

DIRECT WIRE #60

Product: 4110DL, 4110XM, Vista-10SE, Vista-20SE/HWSE, Via-30PSE

Subject: Paging Operation

The Security Systems mentioned above can be programmed to automatically transmit alarm and/or status messages to a compatible pager. This feature requires that you program (select) ADEMCO's Contact ID Reporting format as the primary report format. The message consists of 10-digits: a 4-digit Subscriber No., a 3-digit Event code, and a 3-digit User or Zone Number (i.e., pager displays: 1234-911-004), with each group of digits separated by a hyphen.

When planning to use the paging feature, please be aware that some paging systems may not be compatible with these controls. The controls send an asterisk [\*] in place of each hyphen within the alarm or status message. Some paging systems use the asterisk [\*] key to cancel a message.

To determine whether your pager is compatible with these controls, perform the following: From a touch-tone telephone, send a message to the pager and press the asterisk [\*] key as part of the message. If the message is received, the pager will work. If the message is not received, attempt to send it again. If the test fails twice, the paging system is not compatible.