

VISTA-128FBPN Programming Form

Some fields are programmed for each partition (shown as shaded fields). If you are programming a multiple-partition system, see the *Partition-Specific Fields* section for programming these fields. Standard default (*97) values are shown in brackets []; otherwise, default = 0.

***00** INSTALLER CODE

Enter 4 digits, 0-9 [5140]

***04** ENABLE RANDOM TIMERS

1 2 3 4 5 6 7 8

Enter 1 to make available the randomizing of pre-programmed time driven events for each partition. [0=disable].

Must be "0" for Commercial Burg installations.

***05** SYSTEM EVENTS NOTIFY [0]

1=yes, (messages sent via the RS232 port).

0=no, (no messages sent).

***06** QUICK EXIT [1]

1=enable; 0=disable

***08** TEMPORAL SIREN PULSE – **Not Used at this time.**

***09** ENTRY DELAY #1 [02]

00 (240 seconds), 02-15 times 15 seconds

Maximum "03" for Commercial Burglary installations.

The entry delay time and Abort Window (field *88) combined cannot exceed 60 seconds for SIA installations.

***10** EXIT DELAY #1 [04]

03-15 times 15 seconds

Maximum "04" for Commercial Burglary installations.

Minimum 60 seconds "04" for SIA installations.

***11** ENTRY DELAY #2 [02]

00 (240 seconds), 02-15 times 15 seconds (must be longer than Entry Delay #1). Maximum "03" for Commercial Burglary installations.

The entry delay time and Abort Window (field *88) combined cannot exceed 60 seconds for SIA installations.

***12** EXIT DELAY #2 [04]

03-15 times 15 seconds (must be longer than Exit Delay #1).

Maximum "04" for Commercial Burglary installations.

Minimum 60 seconds "04" for SIA installations.

***13** BELL 1 TIMEOUT [03]

01-15 times 2 minutes. Must be minimum 16 minutes for Commercial Burglary installations. Must be minimum 6 minutes for Commercial Fire and SIA installations.

***14** TRIGGER OR RS232 INPUT [0]

Enter 1 to set J2 Pin 5 as a RS232 input to enable system to receive serial data (75 baud).

Enter 0 to enable J2 Pin 5 as fire alarm trigger.

Must be set to "0".

***15** KEYSWITCH ASSIGNMENT [0]

Enter partition in which keyswitch used, 1-8; 9=silences

Notification Appliance Circuit if fire present; 0=disable

***16** BELL 1 CONFIRMATION OF ARMING DING [1]

1=enable; 0=disable.

NOTE: If using a keyfob, when the button is pressed, either for arming or disarming, the bell will ding indicating that the button is working.

Must be "1" for Commercial Burglary installations.

***17** AC LOSS KEYPAD SOUNDING [1]

1=enable; 0=disable

Must be "1" for Commercial Fire installations.

***19** RANDOMIZE AC LOSS REPORT [2]

0= within 2 minutes; 1=10-40 min; 2=1-3 hours; 3=6-12 hours without Type 13, 1-3 hours with Type 13.

***20** VIP MODULE PHONE CODE - **Not used.**

Enter 01 - 09 for the first digit; enter

[00], [11]

11 for "*" or 12 for "#" for the second digit.

Must be set to "00" for Commercial Burglary and Commercial Fire installations.

***22** KEYPAD PANIC ENABLES [001]

1=enable; 0=disable

995 996 999

NOTE: Use for burglary panic types only. Do not use in partition 1 in Fire systems.

***24** IGNORE EXPANSION ZONE TAMPER [0]

1=Ignore; 0=Enable tamper for RF and V-Plexs.

Must be "0" for Commercial Burglary and Commercial Fire installations if using these devices.

***25** BURG.TRIGGER FOR RESPONSE TYPE 8 [1]

1=enable; 0=disable

***26** INTELLIGENT TEST REPORTING [0]

1=enable (no report sent if any other report was recently sent);

0=disable (send report at programmed interval, field *27)

Must be "0" for Commercial Burglary and Commercial Fire installations.

***27** TEST REPORT INTERVAL [0024]

Enter interval in hours, 0001-9999; 0000=no report;

Max. 0024 for Commercial Burglary and Commercial Fire installations.

***28** POWER UP IN PREVIOUS STATE [1]

1=enable; 0=disable

Must be "1" for Commercial Burglary and Commercial Fire installations.

***29** QUICK ARM [1]

1=enable; 0=disable

***30** MAIN DIALER TOUCHTONE OR ROTARY [1]

1=TouchTone; 0=rotary

***31** PABX ACCESS CODE

00-09; B-F (11-15)

***32** PRIM. SUBS. ACCT #

Enter 00-09; B-F (11-15) [15 15 15 15]

***33 PRIMARY PHONE NUMBER**

 Enter 0-9 for each digit. Enter #11 for *, #12 for #,
 #13 for 2-second pause

***34 SECONDARY PHONE NUMBER**

 Enter 0-9 for each digit. Enter #11 for *, #12 for #,
 #13 for 2-second pause

***35 DOWNLOAD PHONE NO.**

 Enter 0-9 for each digit. Enter #11 for *, #12 for #,
 #13 for 2-second pause

***36 DOWNLOAD ID NO.**

 Enter 00-09; A-F (10-15) [15 15 15 15 15 15 15 15]

***37 DOWNLOAD COMMAND ENABLES**

 Dir ShtdwnSys ShtdwnNot UsedRmt BypRmt DisarmRmt ArmUpdld PgmDwnld Pgm
 See field 1*53 for Callback disable option; [1=enable];
 0=disable. For Commercial Burglary and Commercial Fire
 installations, all entries must be "0."

***38 PREVENT ZONE XXX BYPASS** [000]
 001-128; 000 if all zones can be bypassed

***39 ENABLE OPEN/CLOSE REPORT FOR** [1]
INSTALLER CODE 1=enable; 0=disable

***40 OPEN/CLOSE REPORT FOR KEYSWITCH** [0]
 1=enable; 0=disable

***41 NORMALLY CLOSED or EOLR (Zones 3-8)** [0]
 1=N.C.loops; 0=EOLR supervision.
 Must be "0" for Commercial Burglary and Commercial Fire
 installations.

***42 DIAL TONE PAUSE** [0]
 0=5 seconds; 1=11 seconds; 2=30 seconds.
 Must be "0" Commercial Burglary and Commercial Fire
 installations.

***43 DIAL TONE DETECTION** [1]
 1=wait for true dial tone; 0=pause, then dial

***44 RING DETECTION COUNT** [00]
 01-14; 15=answering machine; 00=no detection.
 Must be "00" for Commercial Burglary and Commercial Fire
 installations.

***45 PRIMARY FORMAT** [1]
 0=Low Speed; 1=Contact ID; 2=ADEMCO High Speed;
 3= ADEMCO Express

***46 LOW SPEED FORMAT (Primary)** [0]
 0= ADEMCO Low Speed; 1=Sescoa/Radionics

***47 SECONDARY FORMAT** [1]
 0=Low Speed; 1=Contact ID; 2= ADEMCO High Speed;
 3= ADEMCO Express

***48 LOW SPEED FORMAT (Sec.)** [0]
 0= ADEMCO Low Speed; 1=Sescoa/Radionics

***49 CHECKSUM VERIFICATION** [0] [0]
 1=enable; 0=disable Prim Sec

***50 SESCOA/RADIONICS SELECT** [0]
 1=Sescoa; 0=Radionics

***51 DUAL REPORTING** [0]
 1=yes; 0=no If used with Spilt Reporting "1" option (1*34),
 alarms and alarm restores go to both primary and secondary
 numbers, while all other reports go to secondary only. If used
 with Split Reporting "2" option, alarms and alarm restores go
 to both, open/close and test messages go to secondary only,
 while all other reports go to primary. If used with Split
 Reporting "3" option, fire alarms and fire restores signals go to
 both, all other reports go to secondary only.

***52 STANDARD/EXPANDED REPORT FOR PRIMARY**
 [0 0 0 0 0 0]
 Alarm Rstr Byp Trbl O/C LoBat
 0=standard; 1=expanded;
NOTE: Expanded overrides 4+2 format.

***53 STANDARD/EXPANDED REPORT FOR SECONDARY**
 [0 0 0 0 0 0]
 Alarm Rstr Byp Trbl O/C LoBat
 0=standard; 1=expanded;
NOTE: Expanded overrides 4+2 format.

***54 UNATTENDED MODE** [1]
 0=disable, 1=enable, if automatic downloads will be allowed
 Must be "0" for Commercial Fire installations.

***56 DYNAMIC SIGNALING DELAY** [03]
 Select the delay time (00-15) times 15 seconds before sending
 to second destination.
NOTE: When Communicator is used as a backup to the dialer,
 the Dynamic Signaling Delay (*56) should be set to a minimum
 of 1 minute.

***57 DYNAMIC SIGNALING PRIORITY** [0]
 0=Primary dialer; 1=Communicator, as first reporting
 destination.
NOTE: Must be set to "0" for SIA installations.

***58 COMM CENTRAL STATION #1 CATEGORY ENABLE**
 [0 0 0 0 0 0]
 Alarm Trbl Byp O/C Syst Test
 0=disable, 1=enable for reports for primary subs ID of
 communicator.

***59 COMM CENTRAL STATION #2 CATEGORY ENABLE**
 [0 0 0 0 0 0]
 Alarm Trbl Byp O/C Syst Test
 0=disable, 1=enable for reports for secondary subs ID of
 communicator.

*77 AUTO TROUBLE RESTORE [1]

0=disable, 1=enable

*79 ZONE TYPE RESTORE ENABLES FOR ZONE TYPES

1-8
1 2 3 4 5 6 7 8

1=enable; [0=disable]

*80 FOR TYPES 9, 10 and 14
9 10 14

1=enable; [0=disable]

Restores must be set to "1" for Commercial Fire installations.

*83 FIRST TEST REPORT TIME

[Day 00; hour 12; min 00]. Days 01-07, Hours 00-23, Min 00-59; 00 in all boxes = instant (Day 01= Monday)

*84 SWINGER SUPPRESSION [01]

01= 1 alarm

02= 2 alarms

NOTE: Fire zones are exempt from this requirement.

Must be "00" (disabled) for Commercial Burglary installations.

*85 ENABLE DIALER REPORTS FOR PANICS & DURESS

1=enable; [0=disable]
995 996 999 Duress

*87 ENTRY WARNING [1]

1=continuous; 0=3 beeps

*88 ABORT WINDOW [2]

1=15 seconds; 2=30 seconds; 3=45 seconds

Must be "0" for Commercial Burglary installations.

Must be "2" for SIA installations.

*89 ALARM RESTORE REPORT TIMING [0]

0 = Restore is sent when zone is restored or at disarming, whichever occurs first.

1 = Restore is sent at disarming whether zone is restored or not, or at bell timeout, but only if restored.

2 = Restore is sent at disarming, whether the zone is restored or not.

This field applies only to Burglary zone types. It does not apply to Fire or Panic zone types.

Must be "2" for Commercial Burglary installations.

*90 SEC. SUBS. ACCT #

Enter 00-09; B-F (11-15) [15 15 15 15]

1*11 ZONE BYPASS AFTER DISARM

[00000000]
1 2 3 4 5 6 7 8

1=enable; 0=disable

Enter 1 for each partition in which zones will remain bypassed after disarm.

NOTES:

For each partition in which field 1*11 is enabled, the **USER CODE + OFF** will no longer unby-pass zones. To unby-pass ALL zones, you must enter **USER CODE + # + 64**. To unby-pass zones INDIVIDUALLY, you must enter **USER CODE + 6 + zone number**.

Any zone that was automatically bypassed by the system will be unby-passed upon disarming of the system (e.g., STAY mode, Auto-STAY, etc.).

Vent zones and zones bypassed by a programmed Auto-Bypass schedule (Timed Driven Event) are considered

"manual bypasses" and will not be unby-passed upon disarming the system.

Zones that were in a bypassed state at the time a System Shutdown is sent from the Compass Downloading software will be unby-passed when the System Shutdown is removed.

1*12 PROGRAM NOTIFICATION SIGNAL [1]

1=yes; 0=no

Must be "1" for Commercial Fire installations.

1*13 SYSTEM SENSOR REVERSING RELAY – Not Used. [0]

0=use neither Zone 1 or Zone 2 inputs; 1=use Zone 1 input; 2=use Zone 2 input; 3=use Zone 1 and Zone 2 inputs.

1*15 CANCEL VERIFY [1]

0=disable, 1=enable alarm output pulse upon kissoff of Cancel report. **NOTE:** Field 1*52 must be enabled to send a Cancel report to the central station.

NOTE: Cancel reports must be enabled in system group 1.

1*17 LOBBY PARTITION [0]

Enter the "common lobby" partition (1-8)

1*18 AFFECTS LOBBY [0]

Enter 1 if this partition affects the common lobby; Enter 0 if it does not.

Must be "0" for Commercial Burglary and Commercial Fire installations.

1*19 ARMS LOBBY [0]

Enter 1 if arming this partition attempts to arm lobby; Enter 0 if it does not.

Must be "0" for Commercial Burglary and Commercial Fire installations.

1*21 EXIT DELAY RESET [1]

0=No; 1=Resets Exit Delay to programmed value after zone is closed and then faulted prior to end of exit delay.

Must be "0" for Commercial Burglary installations. Exit Delay must be enabled "1" for SIA installations.

FIELDS 1*22-1*25: Allow four sets of two zones each to be linked so that both must fault within a 5-minute period to cause an alarm. Default for these fields = [000], [000].

1*22 CROSS-ZONING PAIR ONE

1*23 CROSS-ZONING PAIR TWO

1*24 CROSS-ZONING PAIR THREE

1*25 CROSS-ZONING PAIR FOUR

1*26 PANIC BUTTON OR SPEEDKEY

[00, 00, 00, 00]
A B C D

Enter speedkey macro # (01-32) to use keys A-C for macro. Otherwise enter 00 to use as panic. For D key, enter macro # 01-32, or 00 to select macro when key is pressed.

1*28 RF TX LOW BATTERY SOUND [0]

1=immediate; 0=when disarmed

Must be 1 for UL installations.

1*29 RF TX LOW BATTERY REPORTING [0]

1=enable; 0=disable

Must be 1 for UL installations.

1*30 RF RCVR CHECK-IN INTERVAL [02]

02-15 times 2 hours; 00 disables supervision
Maximum is 2 (4 hr) for UL installations.

1*31 RF XMITTER CHECK-IN INTERVAL [02]

02-15 times 2 hours; 00 disables transmitter supervision
Maximum is 2 (4 hr) for UL installations.

1*33 TOUCHTONE W/ROTARY BACKUP [0]

1=enable; 0=disable

1*34 COMM. SPLIT REPORTING [0]

0=no; 1=alarms and alarm restores primary, others secondary; 2=open/close, test secondary, others primary; 3=fire alarms and fire restores to primary and secondary, all others to secondary. See T51 for comments if using with dual reporting.

NOTE: Split reporting should not be used with Dynamic Signaling.

1*35 ACCESS CONTROL DIALER ENABLES - **Not Used.**

[0 0 0 0 0 0]
Trace Trbl Byp Not Used Syst Alm

1=enable; 0=disable
Must Be Set To "0".

1*42 CALL WAITING DEFEAT [0]

1=enable; 0=disable

1*43 PERM. KEYPAD BACKLIGHT [0]

1=enable; 0=disable, when disabled, display lights when any key is pressed, and turns off after period of keypad inactivity.

1*44 WIRELESS KEYPAD TAMPER DETECTION - **Not Used. Must be set to "0".**

[0]

1=enable; 0=disable.

1*47 CHIME ON BELL 1 [0]

1=enable; 0=disable

1*48 WIRELESS KEYPAD ASSIGNMENT - **Not Used. Must be set to "0".**

[0]

0=disable; enter partition in which RF keypad used, 1-8.

1*49 SUPPRESS TX SUPERVISION SOUND [1]

1=disable; 0=enable.
Must be "0" for Commercial Burglary and Fire installs.

1*53 DOWNLOAD CALLBACK [0]

1=callback not required; 0=callback required.
Must be "0" for Commercial Burglary and Commercial Fire installations.

1*55 EUROPEAN DATE FORMAT [0]

0=disable (mm/dd/yy); 1=enable (dd/mm/yy).

1*56 AC 50/60 Hz CLOCK SPEED [0]

1=50 Hz; 0=60 Hz.

1*57 5800 RF BUTTON GLOBAL ARM [0]

1=enable; 0=disable
Must be "0" for Commercial Burglary and Commercial Fire installations.

1*58 5800 RF BUTTON FORCE ARM [0]

1=enable. If a zone is faulted after pressing button, console will beep once. User should press button again within 4 sec. to force bypass those zones. 0=disable.
Must be "0" for Commercial Burglary and Commercial Fire installations.

1*60 ZONE 5 AUDIO ALARM VERIFICATION [0]

Enter 1 if 2-way audio (AAV) is being used; Enter 0 if it is not.
Must be "0" for Commercial Burglary and Commercial Fire installations.

1*61 ABORT VERIFY [1]

0=disable; 1=enable
Must be enabled "1" for SIA installations.

1*70 EVENT LOG TYPES

[1 0 0 0 1 0]
Alarm Chk Byp O/C Syst Test
1=enable; 0=disable

1*71 12/24 HOUR TIME STAMP FORMAT [0]

0=12 hour; 1=24 hour

1*72 EVENT LOG PRINTER ON-LINE - **Not Used. Must Be Set To "0".**

[0]

0=disable; 1=enable

1*73 PRINTER BAUD RATE - **Not Used. Must Be Set To "0"..**

[0]

1=300; 0=1200

1*74 RELAY TIMEOUT XXX MINUTES [000]

Enter relay timeout, **0-127** in multiples of 2 minutes, desired for #80 Menu Mode time-driven event relay command numbers "04/09" and #93 Menu Mode Output Programming output command "56."

1*75 RELAY TIMEOUT YYY SECONDS [000]

Enter relay timeout, **0-127** seconds, desired for #80 Menu Mode time driven event relay command numbers "05/10" and #93 Menu Mode Output Programming command "57."

1*76 CONTROL RELAY [00]

Relay will be pulsed for 2 seconds whenever code + [0] is pressed. Enter relay number 01-96; 00=none.
Must be "00" for Commercial Burglary and Commercial Fire installations.

1*77 LOG FIRST MAINTENANCE SIGNAL [0]

0=No Log; 1=Log first maintenance signal from each smoke detector.

1*78 EXTENDED HOME CONT EVENTS [0]

Not Used. Must Be Set To "0".
0=Limited home control command set (32 commands).
1=Extended home control command set (255 commands).

1*79 HOME CONTROL EVENTS

[0 0 0 0 0 0]
 Alarm Trbl Byp O/C Syst Test

Not Used. Must Be Set To "0" In Each Entry.
 1=enable; 0=disable. Select the type of events (status reports) transmitted via the RS232 output.

1*80 LOG FAULTS AND RESTORES [1]
 0=Disabled
 1=Enabled

3rd Page Programming Fields (press *94)

2*00 NUMBER OF PARTITIONS [1]
 Enter 1-8

2*01 DAYLIGHT SAVING TIME [03, 11] |
 START/END MONTH Start End
 00-12; if no daylight saving time, enter 00,00

2*02 DAYLIGHT SAVING TIME [2, 1] |
 START/END WEEKEND Start | End
 Enter 1-7. 1=first; 2=second; 3=third; 4=fourth; 5=last; 6=next to last; 7=3rd from last [1,5]

2*05 AUTO-ARM DELAY [15] |
 Enter the time between the end of the arming window and the start of auto-arming warning period, in values of 1-14 times 4 minutes 00=instant; [15=no auto arm at all]. When this delay expires, the Auto-Arm Warning Period begins.

2*06 AUTO-ARM WARNING PERIOD [15] |
 This is the time during which the user is warned to exit the premises prior to the auto-arming of the system (beeps every 15 seconds; "ALERT" displayed). Enter 01-15 minutes. 00=instant at end of arming delay.

2*07 AUTO-DISARM DELAY [15] |
 This is the time between the end of the disarming window and the start of auto-disarming. Enter 01-14 times 4 minutes; 00=instant at end of window; 15=no auto-disarm.

2*08 ENABLE FORCE ARM FOR AUTO-ARM [0]
 0=disable; 1=enable

2*09 OPEN/CLOSE REPORTS BY EXCEPTION [0]
 1=enable; 0=disable
 If enabled, only openings and closings occurring outside the scheduled opening/closing windows will trigger dialer reports. Opening reports will also be suppressed during the closing window, in order to prevent false reports when the user arms the system and then reenters the premises to retrieve a forgotten item.

2*10 ALLOW DISARMING ONLY DURING [0]
 ARMING/DISARMING WINDOWS
 0=disable; 1=enable
 See system-wide field 2*11 if enabling field 2*10. This feature adds high security to the installation.

2*11 ALLOW DISARM OUTSIDE WINDOW [0]
 IF ALARM OCCURS
 Used only if field 2*10 is set to "1." If this field is enabled ("1") the system can be disarmed outside the disarm window if an alarm has occurred. If "0," disarming can only be done during the disarm window. If field 2*10 is set to "0" for a partition, this field has no effect for that partition.

2*18 ENABLE GOTO FOR THIS PARTITION [0]
 1=Allow log-on from other partitions; 0=disable
NOTE: Must be disabled for partition 1 in Commercial Fire installations.

2*19 USE PARTITION DESCRIPTORS [0]
 0=disable; 1=enable

2*20 ENABLE J2 TRIGGERS FOR PARTITION [1]
 0=disable; 1=enable for displayed partition

2*21 ENABLE SUPERVISION PULSES FOR LRR -
Not Used. Must Be Set To "00000".
 00000]
 F B P S T

Used only for supervised connection to non-ECP supported LRR.
 Enter 0 to disable or 1 to enable the listed outputs.
 F= Fire; B= Burglary/Audible Panic; P= Silent Panic/Duress; S= Supervisory; T= Trouble.

2*22 DISPLAY FIRE ALARMS OF [0]
 OTHER PARTITIONS
 0=disable; 1=enable.
 Must be set to "0" (disable) for partition 1.

2*23 DISPLAY BURG, PANIC and CO [0]
 ALARMS OF OTHER PARTITIONS
 0=disable; 1=enable.
 Must be set to "0" (disable) for partition 1.

2*24 DISPLAY TROUBLES OF OTHER [0]
 PARTITIONS
 0=disable; 1=enable
 Must be set to "0" (disable) for partition 1.

4th Page Programming Fields (press *94)

3*00 DISPLAY TRBL INSTEAD OF CHECK [0]
 0=CHECK; 1=TRBL

3*01 EVENTS DISPLAY LOCK [1]
 0=scroll all alarms; 1=lock display of first fire alarm
NOTE: Must be set to "1" for Commercial Fire Installations.

3*12 ZN TYPE 18 DELAY USE [1]
 0=disable; 1=enable
NOTE: Must be set to "0" for Commercial Fire Installations.

3*13 FIRE SUPERVISORY RESPONSE TO OPEN/SHORT
 (Applies to Zone Type 18) [0]
 0=Trouble on open/Supervisory on short
 1=Supervisory on open/Supervisory on short
NOTE: Must be set to "0" for Commercial Fire Installations.

3*14 WATERFLOW SILENCE OPTION [0]
 0=silence on code = off; 1=silence when waterflow restores
NOTE: Must be set to "0" for Commercial Fire Installations.

3*16 DELAY FOR ZONE TYPE 17 & 18 [00] |
 Enter 00-15 times 2 seconds
 Delay cannot exceed 90 seconds in UL installations.
NOTE: Must be "00" for Commercial Fire installations.

3*17 ALTERNATE FUNCTION (TAMPER) [0]
 FOR ZONE 6 0=disable; 1=enable

3*18 EXTENDED DELAY FOR TYPES 17 & 18 [0]

0=disable; 1=enable

NOTE: Must be "0" for Commercial Fire installations.

3*19 AUX INPUT ALTERNATE FUNC ENABLE [0]

0=pins 5 and 9 function as per filed 3*20;

1=pins 5 and 9 function as RXD and DTR

NOTE: Must be set to "0" for Commercial Fire Installations.

3*20 TRIGGER OUTPUT SELECTION [0]

0=Communicator full connection & remote console sounder;

1=Communicator limited connection and keyswitch LEDs

2=Communicator fire only connection and 5140LED

NOTE: Must be set to "0" for Commercial Fire Installations.

3*21 MAX NUMBER OF DIALER ATTEMPTS [8]

1-8 (3, 4 or 5 for NFPA72 compliant systems when a secondary phone number is programmed (field *34))

3*30 DIALER SELECTION [1,0]

0=disable; 1=enable

Main Backup

NOTE: If 3*30 is disabled (0, 0), the panel does not report at all via Communicator.

3*31 BACKUP DIALER TOUCHTONE/ROTARY [0]

1=TouchTone; 0=Rotary

3*50 ZONE TYPE RESTORE ENABLES

FOR ZONE TYPES 16-18

1=enable; [0=disable]

Restores must be set to "1" for Commercial Fire installs.

3*55 RESET ON SECOND OFF FOR BELL 1 [0]

0=disable; 1=enable

NOTE: Must be set to "0" for Commercial Fire Installations.

3*56 RESET ON SECOND OFF FOR BELL 2 [0]

0=disable; 1=enable

NOTE: Must be set to "0" for Commercial Fire Installations.

3*57 BELL 2 & AUX RELAY CONFIRM [0,0]

ARMING DING

Bell 2 Aux

0=disable; 1=enable.

NOTE: If using a keyfob, when the button is pressed, either for arming or disarming, the bell will ding indicating that the button is working.

Must be "1" for Commercial Burglary installations.

3*59 ENABLE BELL 2 & AUX RELAY [0,0]

CHIME ANNUNCIATION

Bell 2 Aux

0=disable; 1=enable

NOTE: Must be "0, 0" if Bell 2 or Aux. Relay is used for fire application.

3*60 BELL 2 & AUX RELAY TIMEOUT

Bell 2 Aux

Enter 00-15 times 2 minutes; 00=no timeout [00,00]

Minimum 16 minutes for Commercial Burglary installations.

3*61 AUX RELAY FUNCTION [1]

0=trouble/supervisory; 1=alarm, silenced by code = off;

2=smoke detector reset; 3=battery save; 4=alarm, silenced

by code = # = 67

NOTE: See Data Field Descriptions in the Installation and Setup Guide for specific information.

3*82 ENABLE BURG FEATURES ON PART 1 [1]

0=disable (disables AWAY, STAY, MAX, TEST, INSTANT and CHIME); 1=enable;

NOTE: Must be "0" for Commercial Fire installations.

3*85 ENABLE FIRE & SYSTEM ZONE BYPASS [1]

0=disable; 1=only installer can bypass;

2=only installer and master can bypass.

Applies to fire zone types 9, 16, 17, and 18 and system zones 970-977 and to partition 1 only.