

Keypad Programming

[000] Keypad Assignment (Section 2.6 "Keypad Assignment")

NOTE: This must be done at each keypad requiring programming.

[0] Partition and Slot [Valid entries are 0 (Global), 1 and 2 for the Partition and 1-8 for the Slot]

[1] Function Key 1 Assignment (Valid entries are 00-18)

[2] Function Key 2 Assignment (Valid entries are 00-18)

[3] Function Key 3 Assignment (Valid entries are 00-18)

[4] Function Key 4 Assignment (Valid entries are 00-18)

[5] Function Key 5 Assignment (Valid entries are 00-18)

00 Null Key (Not Used)

01 Select Partition 1

02 Select Partition 2

03 Stay Arm

04 Away Arm

05 [*][9] No-Entry Arm

06 [*][4] Chime On / Off

07 [*][6][—][4] System Test

08 [*][1] Bypass Mode

09 [*][2] Trouble Display

10 [*][3] Alarm Memory

11 [*][5] User Programming

12 [*][6] User Functions

13 [*][7][1] Utility Output

14 [*][7][2] Sensor Reset

15 General Voice Prompt Help

16 [*][0] Quick Exit

17 [*][1] Reactivate Stay/Away's

18 Identified Voice Prompt Help

	Partiton and Slot (Address)	Function Key 1	Function Key 2	Function Key 3	Function Key 4	Function Key 5
PC55XX Defaults	11	03	04	06	14	16
LCD5500 Defaults	18	03	04	06	14	16
Keypad 1	_____	_____	_____	_____	_____	_____
Keypad 2	_____	_____	_____	_____	_____	_____
Keypad 3	_____	_____	_____	_____	_____	_____
Keypad 4	_____	_____	_____	_____	_____	_____
Keypad 5	_____	_____	_____	_____	_____	_____
Keypad 6	_____	_____	_____	_____	_____	_____
Keypad 7	_____	_____	_____	_____	_____	_____
Keypad 8	_____	_____	_____	_____	_____	_____

Basic System Programming

Zone Definitions

- | | | |
|---|---------------------------------------|--|
| 00 Null Zone (Not Used) | 09 24 Hour Supervisory (LINKS) | 18 24 Hour Sprinkler |
| 01 Delay 1 | 10 24 Hour Supervisory Buzzer | 19 24 Hour Water |
| 02 Delay 2 | 11 24 Hour Burglary | 20 24 Hour Freeze |
| 03 Instant | 12 24 Hour Holdup | 21 24 Hour Latching Tamper |
| 04 Interior | 13 24 Hour Gas | 22 Momentary Keyswitch Arm |
| 05 Interior, Stay/Away | 14 24 Hour Heat | 23 Maintained Keyswitch Arm |
| 06 Delay, Stay/Away | 15 24 Hour Medical | 24 LINKS Answer |
| 07 Delayed 24 Hour Fire (Hardwired) | 16 24 Hour Panic | 25 Interior Delay |
| 08 Standard 24 Hour Fire (Hardwired) | 17 24 Hour Emergency | 87 Delay 24 Hour Fire (Wireless) |
| | | 88 Standard 24 Hour Fire (Wireless) |

[001] Zone 1-8 Definitions (Section 5.1 "Zone Definitions")

Default		Default	
01	<input type="text"/>	04	<input type="text"/>
	Zone 1		Zone 5
03	<input type="text"/>	04	<input type="text"/>
	Zone 2		Zone 6
03	<input type="text"/>	04	<input type="text"/>
	Zone 3		Zone 7
03	<input type="text"/>	04	<input type="text"/>
	Zone 4		Zone 8

[002] Zone 9-16 Definitions (Section 5.1 "Zone Definitions")

Default		Default	
00	<input type="text"/>	00	<input type="text"/>
	Zone 9		Zone 13
00	<input type="text"/>	00	<input type="text"/>
	Zone 10		Zone 14
00	<input type="text"/>	00	<input type="text"/>
	Zone 11		Zone 15
00	<input type="text"/>	00	<input type="text"/>
	Zone 12		Zone 16

[003] Zone 17-24 Definitions (Section 5.1 "Zone Definitions")

Default		Default	
00	<input type="text"/>	00	<input type="text"/>
	Zone 17		Zone 21
00	<input type="text"/>	00	<input type="text"/>
	Zone 18		Zone 22
00	<input type="text"/>	00	<input type="text"/>
	Zone 19		Zone 23
00	<input type="text"/>	00	<input type="text"/>
	Zone 20		Zone 24

[004] Zone 25-32 Definitions (Section 5.1 "Zone Definitions")

Default		Default	
00	<input type="text"/>	00	<input type="text"/>
	Zone 25		Zone 29
00	<input type="text"/>	00	<input type="text"/>
	Zone 26		Zone 30
00	<input type="text"/>	00	<input type="text"/>
	Zone 27		Zone 31
00	<input type="text"/>	00	<input type="text"/>
	Zone 28		Zone 32

[005] System Times

Default	[001-255]	
030	<input type="text"/>	Entry Delay 1 (in seconds)
045	<input type="text"/>	Entry Delay 2 (in seconds)
060	<input type="text"/>	Exit Delay (in seconds)
010	<input type="text"/>	Bell Cut-off (in minutes)

[006] Installer's Code (Section 4.1 "How to Enter Installer Programming")

Default

5010

[007] Master Code (Section 3.1 "Access Codes")

Default

1234

[008] Maintenance Code (Section 3.1 "Access Codes")

Default

AAAA

Programmable Output Options

- | | |
|--|--|
| 00 Not used | 10 Latched System Event [Strobe (with Event options)] |
| 01 Burglary and Fire Bell Output | 11 System Tamper (all sources: zones, kpd, modules) |
| 02 Utility Output | 12 TLM and Alarm |
| 03 Sensor Reset | 13 Kissoff Output |
| 04 2-Wire Smoke Support (PGM2 ONLY) | 14 Ground Start Pulse |
| 05 System (Partition) Armed Status | 15 For Future Use |
| 06 Ready To Arm | 16 LINKS1000 Support (PGM 1 only) |
| 07 Keypad Buzzer Follow Mode | 17 Away Arm |
| 08 Courtesy Pulse | 18 Stay Arm |
| 09 System Trouble Output (with Trouble options) | |

[009] PC5010 PGM Output Programming (PGM 1 & 2) (Section 5.10 "PGM Outputs")

Default

02 PGM 1

10 PGM 2

[010] PC5208 PGM Output Programming (PGM 3-10) (Section 5.10 "PGM Outputs")

Default

01 PGM 3

01 PGM 4

01 PGM 5

01 PGM 6

Default

01 PGM 7

01 PGM 8

01 PGM 9

01 PGM 10

[011] PC5204 PGM Output Programming (PGM 11-14) (Section 5.10 "PGM Outputs")

Default

01 PGM 11

01 PGM 12

01 PGM 13

01 PGM 14

[012] Keypad Lockout Options (Section 5.22 "Keypad Lockout")

Default

000 Number of Invalid Codes Before Lockout

000 Lockout Duration (in minutes)

[013] First System Option Code

Default	Option	ON	Off	Section
OFF	<input type="checkbox"/>	1	Normally Closed Loops	End-of-Line Resistors 2.9
OFF	<input type="checkbox"/>	2	Double End-of-Line Resistors	Single End-of-Line Resistors 2.9
ON	<input type="checkbox"/>	3	On-board Zones 1-4 enabled	On-board Zones 1-4 disabled 5.27
ON	<input type="checkbox"/>	4	On-board Zones 5-8 enabled	On-board Zones 5-8 disabled 5.27
OFF	<input type="checkbox"/>	5	Zone 8 is Fast Loop Response	Zone 8 is Standard Loop Response 5.24
OFF	<input type="checkbox"/>	6	For Future Use	
ON	<input type="checkbox"/>	7	Event Buffer Follows Swinger Shutdown	Event Buffer Logs Events Past shutdown 5.17
OFF	<input type="checkbox"/>	8	For Future Use	

[014] Second System Option Code

Default	Option	ON	Off	Section
OFF	<input type="checkbox"/>	1	Arm / Disarm Bell Squawk enabled	Arm / Disarm Bell Squawk disabled 5.20
OFF	<input type="checkbox"/>	2	Bell Squawk During Auto Arm	No Bell Squawk During Auto Arm 5.21
OFF	<input type="checkbox"/>	3	Bell Squawk On Exit Delay	No Bell Squawk On Exit Delay 5.15
OFF	<input type="checkbox"/>	4	Bell Squawk On Entry Delay	No Bell Squawk On Entry Delay 5.15
OFF	<input type="checkbox"/>	5	Bell Squawk On Trouble	No Bell Squawk On Trouble 3.4
ON	<input type="checkbox"/>	6	Audible Exit Beeps	Silent Exit Delay 5.15
OFF	<input type="checkbox"/>	7	Exit Delay Termination Enabled	Exit Delay Termination Disabled 5.15
OFF	<input type="checkbox"/>	8	Fire Bell is continuous	Fire Bell follows Bell Cut-off 5.1

[015] Third System Option Code

Default	Option	ON	Off	Section
ON	<input type="checkbox"/>	1	Fire Keys Enabled	Fire Keys Disabled 5.14
OFF	<input type="checkbox"/>	2	Panic Keys Audible (Bell / Beeps)	Panic Keys Silent 5.14
OFF	<input type="checkbox"/>	3	Quick Exit Enabled	Quick Exit Disabled 3.4
ON	<input type="checkbox"/>	4	Quick Arming Enabled	Quick Arming Disabled 3.4
OFF	<input type="checkbox"/>	5	Code Required For Bypassing	No Code Required 3.4
OFF	<input type="checkbox"/>	6	Master Code Not Changeable	Master Code Changeable 3.1
ON	<input type="checkbox"/>	7	TLM Enabled	TLM Disabled 5.11
ON	<input type="checkbox"/>	8	TLM Audible When Armed	TLM Trouble Only When Armed 5.11

[016] Fourth System Option Code

Default	Option	ON	Off	Section
ON	<input type="checkbox"/>	1	AC Trouble Displayed	AC Trouble Not Displayed 3.4
OFF	<input type="checkbox"/>	2	Trouble Light Flashes if AC Fails	Trouble Light Does Not Follow AC Status 3.4
OFF	<input type="checkbox"/>	3	Blank Keypad When Not Used	Keypad Active Always 5.23
OFF	<input type="checkbox"/>	4	Code Required to Remove Kypd Blanking	No Code Required 5.23
ON	<input type="checkbox"/>	5	Keypad Backlighting is enabled	Keypad Backlighting is disabled 5.19
OFF	<input type="checkbox"/>	6	Power Save Mode enabled	Power Save Mode disabled 5.23
OFF	<input type="checkbox"/>	7	Bypass Status Displayed While Armed	Bypass Status Not Displayed While Armed 3.4
OFF	<input type="checkbox"/>	8	Keypad Tamper enabled	Keypad Tamper disabled 5.25

Advanced System Programming

Zone Attribute Defaults

	00	01	02	03	04	05	06	07	08	09	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	87	88
	Null Zone (Not Used)	Delay 1	Delay 2	Instant	Interior	Interior, Stay/Away	Delay, Stay/Away	Delayed 24hr Fire (Hardw.)	Standard 24hr Fire (Hardw.)	24hr Supervisory (LINKS)	24hr Supervisory Buzzer	24hr Burglary	24hr Holdup	24hr Gas	24hr Heat	24hr Medical	24hr Panic	24hr Emergency	24hr Sprinkler	24hr Water	24hr Freeze	24hr Latching Tamper	Momentary Keyswitch	Maintained Keyswitch	LINKS Answer	Interior Delay	Delayed 24hr Fire (Wireless)	Standard 24hr Fire (Wireless)
Option 1 – Audible / Silent	N	Y	Y	Y	Y	Y	Y	Y	Y	N	N	Y	N	Y	Y	Y	Y	Y	Y	Y	Y	Y	N	N	N	Y	Y	Y
Option 2 – Steady / Pulsed	N	Y	Y	Y	Y	Y	Y	N	N	Y	Y	Y	Y	N	N	Y	Y	Y	Y	Y	Y	Y	N	N	N	Y	N	N
Option 3 – Chime	N	Y	Y	Y	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N
Option 4 – Bypass	N	Y	Y	Y	Y	Y	Y	N	N	N	Y	Y	N	N	N	N	N	N	N	N	N	N	N	N	N	Y	N	N
Option 5 – Force	N	N	N	N	N	Y	Y	N	N	Y	N	N	N	N	N	N	N	N	N	N	N	N	Y	Y	Y	N	N	N
Option 6 – Swing	N	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Option 7 – Tx. Delay	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N
Option 8 – Wireless Zone	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	Y	Y

Y = Option ON **N = Option OFF**

Zone 1-32 Attributes (Section 5.2 "Zone Attributes")

	ON	Opt 1	Opt 2	Opt 3	Opt 4	Opt 5	Opt 6	Opt 7	Opt 8
	OFF	Audible	Steady	Chime	Bypass	Force	Swing	Tx Del.	Wireless
		Silent	Pulsed	No	No	No	No	No	Zone
[101] Zone 1		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[102] Zone 2		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[103] Zone 3		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[104] Zone 4		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[105] Zone 5		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[106] Zone 6		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[107] Zone 7		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[108] Zone 8		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[109] Zone 9		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[110] Zone 10		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[111] Zone 11		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[112] Zone 12		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[113] Zone 13		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[114] Zone 14		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[115] Zone 15		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[116] Zone 16		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[117] Zone 17		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[118] Zone 18		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[119] Zone 19		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[120] Zone 20		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[121] Zone 21		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[122] Zone 22		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[123] Zone 23		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[124] Zone 24		<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

	Opt 1	Opt 2	Opt 3	Opt 4	Opt 5	Opt 6	Opt 7	Opt 8
[125] Zone 25	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[126] Zone 26	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[127] Zone 27	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[128] Zone 28	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[129] Zone 29	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[130] Zone 30	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[131] Zone 31	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[132] Zone 32	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

PGM Attributes (Section 5.10 "PGM Outputs")

Program only the following attributes for the PGM Options listed. All others will be ignored. PGM Options are programmed in sections [009], [010], [011].

PGM Options 1, 8, 11-16:

Attribute 3 - Option Activates/Deactivates Output

PGM Option 4 (2-Wire Smoke Support): None

PGM Option 9 (System Trouble Output):

Attribute 1 - Service Required

Attribute 2 - AC Fail

Attribute 3 - Telephone Line Fault

Attribute 4 - Dialer - Failure to Communicate

Attribute 5 - Fire Zone Fault

Attribute 6 - Zone Tamper

Attribute 7 - Zone Low Battery

Attribute 8 - Loss of Clock

PGM Options 2, 3, 5-7, 17, 18:

Attribute 1 - Partition 1 Controls Event,

Attribute 2 - Partition 2 Controls Event,

Attribute 3 - Option Activates/Deactivates Output

PGM Option 10 Latched System Event

Attribute 1 - Burglary

Attribute 2 - Fire

Attribute 3 - Panic

Attribute 4 - Medical

Attribute 5 - Supervisory

Attribute 6 - Priority

Attribute 7 - Holdup

Attribute	1	2	3	4	5	6	7	8
Default	ON	ON	ON	ON	ON	ON	ON	ON

PC5010

[141] PGM 1	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[142] PGM 2	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

PC5208

[143] PGM 3	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[144] PGM 4	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[145] PGM 5	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[146] PGM 6	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[147] PGM 7	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[148] PGM 8	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[149] PGM 9	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[150] PGM 10	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

PC5204

[151] PGM 11	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[152] PGM 12	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[153] PGM 13	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
[154] PGM 14	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

[160] Maximum Dialing Attempts to Each Phone Number (Section 5.3 "Communicator Dialing")

Default: 003 Valid entries are 001-255 attempts (Do not enter 000)

[161] Post Dial Wait for Handshake (All Formats) (Section 5.3 "Communicator Dialing")

Default: 040 Valid entries are 001-255 seconds

[162] No Activity Arming (Partition 1) (Section 5.21 "Automatic Arming")

Default: 000 Valid entries are 000-255 minutes (000 = disabled)

[163] No Activity Arming (Partition 2) (Section 5.21 "Automatic Arming")

Default: 000 Valid entries are 000-255 minutes (000 = disabled)

Zone Programming

[201] First Partition Option Code (Section 5.9 "Partition/Zone Assignment")

Default	Option	ON	OFF
OFF <input type="checkbox"/>	1	Partition 2 is Enabled	Partition 2 is Disabled
OFF <input type="checkbox"/>	2-8	For Future Use	

[202] Partition 1 Zone Assignments (1-8) (Section 5.9 "Partition/Zone Assignment")

Default	Option	ON	OFF
ON <input type="checkbox"/>	1	Zone 1 is on Partition 1	Zone 1 is not on Partition 1
ON <input type="checkbox"/>	2	Zone 2 is on Partition 1	Zone 2 is not on Partition 1
ON <input type="checkbox"/>	3	Zone 3 is on Partition 1	Zone 3 is not on Partition 1
ON <input type="checkbox"/>	4	Zone 4 is on Partition 1	Zone 4 is not on Partition 1
ON <input type="checkbox"/>	5	Zone 5 is on Partition 1	Zone 5 is not on Partition 1
ON <input type="checkbox"/>	6	Zone 6 is on Partition 1	Zone 6 is not on Partition 1
ON <input type="checkbox"/>	7	Zone 7 is on Partition 1	Zone 7 is not on Partition 1
ON <input type="checkbox"/>	8	Zone 8 is on Partition 1	Zone 8 is not on Partition 1

[203] Partition 1 Zone Assignments (9-16) (Section 5.9 "Partition/Zone Assignment")

Default	Option	ON	OFF
OFF <input type="checkbox"/>	1	Zone 9 is on Partition 1	Zone 9 is not on Partition 1
OFF <input type="checkbox"/>	2	Zone 10 is on Partition 1	Zone 10 is not on Partition 1
OFF <input type="checkbox"/>	3	Zone 11 is on Partition 1	Zone 11 is not on Partition 1
OFF <input type="checkbox"/>	4	Zone 12 is on Partition 1	Zone 12 is not on Partition 1
OFF <input type="checkbox"/>	5	Zone 13 is on Partition 1	Zone 13 is not on Partition 1
OFF <input type="checkbox"/>	6	Zone 14 is on Partition 1	Zone 14 is not on Partition 1
OFF <input type="checkbox"/>	7	Zone 15 is on Partition 1	Zone 15 is not on Partition 1
OFF <input type="checkbox"/>	8	Zone 16 is on Partition 1	Zone 16 is not on Partition 1

[204] Partition 1 Zone Assignments (17-24) (Section 5.9 "Partition/Zone Assignment")

Default	Option	ON	OFF
OFF <input type="checkbox"/>	1	Zone 17 is on Partition 1	Zone 17 is not on Partition 1
OFF <input type="checkbox"/>	2	Zone 18 is on Partition 1	Zone 18 is not on Partition 1
OFF <input type="checkbox"/>	3	Zone 19 is on Partition 1	Zone 19 is not on Partition 1
OFF <input type="checkbox"/>	4	Zone 20 is on Partition 1	Zone 20 is not on Partition 1
OFF <input type="checkbox"/>	5	Zone 21 is on Partition 1	Zone 21 is not on Partition 1
OFF <input type="checkbox"/>	6	Zone 22 is on Partition 1	Zone 22 is not on Partition 1
OFF <input type="checkbox"/>	7	Zone 23 is on Partition 1	Zone 23 is not on Partition 1
OFF <input type="checkbox"/>	8	Zone 24 is on Partition 1	Zone 24 is not on Partition 1

[205] Partition 1 Zone Assignments (25-32) (Section 5.9 "Partition/Zone Assignment")

Default	Option	ON	OFF
OFF <input type="checkbox"/>	1	Zone 25 is on Partition 1	Zone 25 is not on Partition 1
OFF <input type="checkbox"/>	2	Zone 26 is on Partition 1	Zone 26 is not on Partition 1
OFF <input type="checkbox"/>	3	Zone 27 is on Partition 1	Zone 27 is not on Partition 1
OFF <input type="checkbox"/>	4	Zone 28 is on Partition 1	Zone 28 is not on Partition 1
OFF <input type="checkbox"/>	5	Zone 29 is on Partition 1	Zone 29 is not on Partition 1
OFF <input type="checkbox"/>	6	Zone 30 is on Partition 1	Zone 30 is not on Partition 1
OFF <input type="checkbox"/>	7	Zone 31 is on Partition 1	Zone 31 is not on Partition 1
OFF <input type="checkbox"/>	8	Zone 32 is on Partition 1	Zone 32 is not on Partition 1

[206] Partition 2 Zone Assignments (1-8) (Section 5.9 "Partition/Zone Assignment")

Default		Option	ON	OFF
OFF	<input type="checkbox"/>	1	Zone 1 is on Partition 2	Zone 1 is not on Partition 2
OFF	<input type="checkbox"/>	2	Zone 2 is on Partition 2	Zone 2 is not on Partition 2
OFF	<input type="checkbox"/>	3	Zone 3 is on Partition 2	Zone 3 is not on Partition 2
OFF	<input type="checkbox"/>	4	Zone 4 is on Partition 2	Zone 4 is not on Partition 2
OFF	<input type="checkbox"/>	5	Zone 5 is on Partition 2	Zone 5 is not on Partition 2
OFF	<input type="checkbox"/>	6	Zone 6 is on Partition 2	Zone 6 is not on Partition 2
OFF	<input type="checkbox"/>	7	Zone 7 is on Partition 2	Zone 7 is not on Partition 2
OFF	<input type="checkbox"/>	8	Zone 8 is on Partition 2	Zone 8 is not on Partition 2

[207] Partition 2 Zone Assignments (9-16) (Section 5.9 "Partition/Zone Assignment")

Default		Option	ON	OFF
OFF	<input type="checkbox"/>	1	Zone 9 is on Partition 2	Zone 9 is not on Partition 2
OFF	<input type="checkbox"/>	2	Zone 10 is on Partition 2	Zone 10 is not on Partition 2
OFF	<input type="checkbox"/>	3	Zone 11 is on Partition 2	Zone 11 is not on Partition 2
OFF	<input type="checkbox"/>	4	Zone 12 is on Partition 2	Zone 12 is not on Partition 2
OFF	<input type="checkbox"/>	5	Zone 13 is on Partition 2	Zone 13 is not on Partition 2
OFF	<input type="checkbox"/>	6	Zone 14 is on Partition 2	Zone 14 is not on Partition 2
OFF	<input type="checkbox"/>	7	Zone 15 is on Partition 2	Zone 15 is not on Partition 2
OFF	<input type="checkbox"/>	8	Zone 16 is on Partition 2	Zone 16 is not on Partition 2

[208] Partition 2 Zone Assignments (17-24) (Section 5.9 "Partition/Zone Assignment")

Default		Option	ON	OFF
OFF	<input type="checkbox"/>	1	Zone 17 is on Partition 2	Zone 17 is not on Partition 2
OFF	<input type="checkbox"/>	2	Zone 18 is on Partition 2	Zone 18 is not on Partition 2
OFF	<input type="checkbox"/>	3	Zone 19 is on Partition 2	Zone 19 is not on Partition 2
OFF	<input type="checkbox"/>	4	Zone 20 is on Partition 2	Zone 20 is not on Partition 2
OFF	<input type="checkbox"/>	5	Zone 21 is on Partition 2	Zone 21 is not on Partition 2
OFF	<input type="checkbox"/>	6	Zone 22 is on Partition 2	Zone 22 is not on Partition 2
OFF	<input type="checkbox"/>	7	Zone 23 is on Partition 2	Zone 23 is not on Partition 2
OFF	<input type="checkbox"/>	8	Zone 24 is on Partition 2	Zone 24 is not on Partition 2

[209] Partition 2 Zone Assignments (25-32) (Section 5.9 "Partition/Zone Assignment")

Default		Option	ON	OFF
OFF	<input type="checkbox"/>	1	Zone 25 is on Partition 2	Zone 25 is not on Partition 2
OFF	<input type="checkbox"/>	2	Zone 26 is on Partition 2	Zone 26 is not on Partition 2
OFF	<input type="checkbox"/>	3	Zone 27 is on Partition 2	Zone 27 is not on Partition 2
OFF	<input type="checkbox"/>	4	Zone 28 is on Partition 2	Zone 28 is not on Partition 2
OFF	<input type="checkbox"/>	5	Zone 29 is on Partition 2	Zone 29 is not on Partition 2
OFF	<input type="checkbox"/>	6	Zone 30 is on Partition 2	Zone 30 is not on Partition 2
OFF	<input type="checkbox"/>	7	Zone 31 is on Partition 2	Zone 31 is not on Partition 2
OFF	<input type="checkbox"/>	8	Zone 32 is on Partition 2	Zone 32 is not on Partition 2

Communicator Programming

NOTE: For sections [301] to [352], the contents of every section by default is [F].

[301] First Telephone Number (32 Digits) (Section 5.4 "Communicator – Phone Numbers")

[302] Second Telephone Number (32 Digits) (Section 5.4 "Communicator – Phone Numbers")

[303] Third Telephone Number (32 Digits) (Section 5.4 "Communicator – Phone Numbers")

[310] Partition 1 Identifier Code (Section 5.5 "Communicator – Account Numbers")

[311] Partition 2 Identifier Code (Section 5.5 "Communicator – Account Numbers")

[320] Alarm Reporting Codes, Zones 1-8 (Section 5.7 "Communicator – Reporting Codes")

Default

3 4 _____ Zone 1

3 A _____ Zone 2

3 A _____ Zone 3

3 A _____ Zone 4

Default

3 A _____ Zone 5

3 A _____ Zone 6

3 A _____ Zone 7

3 A _____ Zone 8

[321] Alarm Reporting Codes, Zones 9-16 (Section 5.7 "Communicator – Reporting Codes")

Default

3 A _____ Zone 9

3 A _____ Zone 10

3 A _____ Zone 11

3 A _____ Zone 12

Default

3 A _____ Zone 13

3 A _____ Zone 14

3 A _____ Zone 15

3 A _____ Zone 16

[322] Alarm Reporting Codes, Zones 17-24 (Section 5.7 "Communicator – Reporting Codes")

Default

3 A _____ Zone 17

3 A _____ Zone 18

3 A _____ Zone 19

3 A _____ Zone 20

Default

3 A _____ Zone 21

3 A _____ Zone 22

3 A _____ Zone 23

3 A _____ Zone 24

[323] Alarm Reporting Codes, Zones 25-32 (Section 5.7 "Communicator – Reporting Codes")

Default

3 A _____ Zone 25

3 A _____ Zone 26

3 A _____ Zone 27

3 A _____ Zone 28

Default

3 A _____ Zone 29

3 A _____ Zone 30

3 A _____ Zone 31

3 A _____ Zone 32

[324] Alarm Restoral Reporting Codes, Zones 1-8 (Section 5.7 "Communicator – Reporting Codes")

Default

3 4 _____ Zone 1

3 A _____ Zone 2

3 A _____ Zone 3

3 A _____ Zone 4

Default

3 A _____ Zone 5

3 A _____ Zone 6

3 A _____ Zone 7

3 A _____ Zone 8

[325] Alarm Restoral Reporting Codes, Zones 9-16 (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
3 A	_____	Zone 9	3 A _____ Zone 13
3 A	_____	Zone 10	3 A _____ Zone 14
3 A	_____	Zone 11	3 A _____ Zone 15
3 A	_____	Zone 12	3 A _____ Zone 16

[326] Alarm Restoral Reporting Codes, Zones 17-24 (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
3 A	_____	Zone 17	3 A _____ Zone 21
3 A	_____	Zone 18	3 A _____ Zone 22
3 A	_____	Zone 19	3 A _____ Zone 23
3 A	_____	Zone 20	3 A _____ Zone 24

[327] Alarm Restoral Reporting Codes, Zones 25-32 (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
3 A	_____	Zone 25	3 A _____ Zone 29
3 A	_____	Zone 26	3 A _____ Zone 30
3 A	_____	Zone 27	3 A _____ Zone 31
3 A	_____	Zone 28	3 A _____ Zone 32

[328] Miscellaneous Alarm Reporting Codes (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
2 1	_____	Duress Alarm	4 3 _____ Zone Expander Supervisory Alarm
F F	_____	Opening After Alarm	4 3 _____ Zone Expander Supervisory Restoral
F F	_____	Recent Closing	

[329] Priority Alarm and Restoral (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
1 5	_____	Keypad Fire Alarm	1 5 _____ Keypad Fire Restoral
A A	_____	Keypad Auxiliary Alarm	A A _____ Keypad Auxiliary Restoral
2 A	_____	Keypad Panic Alarm	2 A _____ Keypad Panic Restoral
1 1	_____	2 Wire Smoke Alarm	1 1 _____ 2 Wire Smoke Restoral

[330] Tamper Reporting Codes, Zones 1-8 (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
4 4	_____	Zone 1	4 4 _____ Zone 5
4 4	_____	Zone 2	4 4 _____ Zone 6
4 4	_____	Zone 3	4 4 _____ Zone 7
4 4	_____	Zone 4	4 4 _____ Zone 8

[331] Tamper Reporting Codes, Zones 9-16 (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
4 4	_____	Zone 9	4 4 _____ Zone 13
4 4	_____	Zone 10	4 4 _____ Zone 14
4 4	_____	Zone 11	4 4 _____ Zone 15
4 4	_____	Zone 12	4 4 _____ Zone 16

[332] Tamper Reporting Codes, Zones 17-24 (Section 5.7 "Communicator – Reporting Codes")

Default

4 4 Zone 17
4 4 Zone 18
4 4 Zone 19
4 4 Zone 20

Default

4 4 Zone 21
4 4 Zone 22
4 4 Zone 23
4 4 Zone 24

[333] Tamper Reporting Codes, Zones 25-32 (Section 5.7 "Communicator – Reporting Codes")

Default

4 4 Zone 25
4 4 Zone 26
4 4 Zone 27
4 4 Zone 28

Default

4 4 Zone 29
4 4 Zone 30
4 4 Zone 31
4 4 Zone 32

[334] Tamper Restoral Reporting Codes, Zones 1-8 (Section 5.7 "Communicator – Reporting Codes")

Default

4 4 Zone 1
4 4 Zone 2
4 4 Zone 3
4 4 Zone 4

Default

4 4 Zone 5
4 4 Zone 6
4 4 Zone 7
4 4 Zone 8

[335] Tamper Restoral Reporting Codes, Zones 9-16 (Section 5.7 "Communicator – Reporting Codes")

Default

4 4 Zone 9
4 4 Zone 10
4 4 Zone 11
4 4 Zone 12

Default

4 4 Zone 13
4 4 Zone 14
4 4 Zone 15
4 4 Zone 16

[336] Tamper Restoral Reporting Codes, Zones 17-24 (Section 5.7 "Communicator – Reporting Codes")

Default

4 4 Zone 17
4 4 Zone 18
4 4 Zone 19
4 4 Zone 20

Default

4 4 Zone 21
4 4 Zone 22
4 4 Zone 23
4 4 Zone 24

[337] Tamper Restoral Reporting Codes, Zones 25-32 (Section 5.7 "Communicator – Reporting Codes")

Default

4 4 Zone 25
4 4 Zone 26
4 4 Zone 27
4 4 Zone 28

Default

4 4 Zone 29
4 4 Zone 30
4 4 Zone 31
4 4 Zone 32

[338] Miscellaneous Tamper Reporting Codes (Section 5.7 "Communicator – Reporting Codes")

Default

4 5 General System Tamper
4 5 General System Tamper Rest.
2 1 Keypad Lockout

[339] Closing (Arming) Reporting Codes, Access Codes 1-8 (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>

[340] Closing (Arming) Reporting Codes, Access Codes 9-16 (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>

[341] Closing (Arming) Reporting Codes, Access Codes 17-24 (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>

[342] Closing (Arming) Reporting Codes, Access Codes 25-32 (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>

[343] Miscellaneous Closing (Arming) Reporting Codes (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	7 A	<input type="text"/>
A 2	<input type="text"/>	A A	<input type="text"/>
A 2	<input type="text"/>		

[344] Opening (Disarming) Reporting Codes, Access Codes 1-8 (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>

[345] Opening (Disarming) Reporting Codes, Access Codes 9-16 (Section 5.7 "Communicator – Reporting Codes")

Default		Default	
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>
A 2	<input type="text"/>	A 2	<input type="text"/>

[346] Opening (Disarming) Reporting Codes, Access Codes 17-24
(Section 5.7 "Communicator – Reporting Codes")

Default		Default			
A 2		Code 17	A 2		Code 21
A 2		Code 18	A 2		Code 22
A 2		Code 19	A 2		Code 23
A 2		Code 20	A 2		Code 24

[347] Opening (Disarming) Reporting Codes, Access Codes 25-32
(Section 5.7 "Communicator – Reporting Codes")

Default		Default			
A 2		Code 25	A 2		Code 29
A 2		Code 26	A 2		Code 30
A 2		Code 27	A 2		Code 31
A 2		Code 28	A 2		Code 32

[348] Miscellaneous Opening (Disarming) Reporting Codes (Section 5.7 "Communicator – Reporting Codes")

Default		Default			
A 2		Opening by Duress Code 33	A 2		Opening by System Code 42
A 2		Opening by Duress Code 34	A 5		Auto Arm Cancellation
A 2		Opening by System Code 40	A A		Special Opening
A 2		Opening by System Code 41			

[349] Maintenance Alarm Reporting Codes (Section 5.7 "Communicator – Reporting Codes")

Default		Default			
A 2		Battery Trouble Alarm	A A		Auxiliary Power Supply Trouble Alarm
A 1		AC Failure Trouble Alarm	5 1		TLM Trouble Code (via LINKS)
2 1		Bell Circuit Trouble Alarm	A A		General System Trouble
7 3		Fire Trouble Alarm	3 3		General System Supervisory

[350] Maintenance Restoral Reporting Codes (Section 5.7 "Communicator – Reporting Codes")

Default		Default			
A 2		Battery Trouble Restoral	A A		Auxiliary Power Supply Trouble Restoral
A 1		AC Failure Trouble Restoral	5 1		TLM Restoral
2 1		Bell Circuit Trouble Restoral	A A		General System Trouble Restore
7 3		Fire Trouble Restoral	3 3		General System Supervisory Restore

[351] Miscellaneous Maintenance Reporting Codes (Section 5.7 "Communicator – Reporting Codes")

Default		
5 4		Phone Number 1 Failure to Communicate
5 4		Phone Number 2 Failure to Communicate
F F		Event Buffer is 75% Full Since Last Upload
1 1		DLS Lead IN
1 2		DLS Lead OUT
7 2		General Zone Trouble Alarm
7 2		General Zone Trouble Restore

[352] Test Transmission Reporting Codes (Section 5.7 "Communicator – Reporting Codes")

Default		Default			
A 2		Periodic Test Transmission	A 3		LINKS1000 Test Transmission Code
F F		System Test			

[353] Wireless Maintenance Reporting Codes (Section 5.7 "Communicator – Reporting Codes")

Default	Default
8 4 <input type="checkbox"/> <input type="checkbox"/> General Zone Low Battery Alarm	8 4 <input type="checkbox"/> <input type="checkbox"/> General Zone Low Battery Restore

[360] Communicator Format Options (Section 5.6 "Communicator – Reporting Formats")

Default	
0 3 <input type="checkbox"/> <input type="checkbox"/> 1st Phone Number	
0 3 <input type="checkbox"/> <input type="checkbox"/> 2nd Phone Number	
03 DTMF CONTACT I.D.	04 SIA FSK
	05 Residential Dial

[361] Partition 1 Alarms and Restorals (Section 5.3 "Communicator – Dialing")

Default	Option	ON	OFF
ON <input type="checkbox"/>	1	1st Telephone Number	Disabled
OFF <input type="checkbox"/>	2	2nd Telephone Number	Disabled
OFF <input type="checkbox"/>	3	1st Telephone Number (via LINKS)	Disabled
OFF <input type="checkbox"/>	4	2nd Telephone Number (via LINKS)	Disabled
OFF <input type="checkbox"/>	5-8	For Future Use	

[362] Partition 2 Alarms and Restorals (Section 5.3 "Communicator – Dialing")

Default	Option	ON	OFF
ON <input type="checkbox"/>	1	1st Telephone Number	Disabled
OFF <input type="checkbox"/>	2	2nd Telephone Number	Disabled
OFF <input type="checkbox"/>	3	1st Telephone Number (via LINKS)	Disabled
OFF <input type="checkbox"/>	4	2nd Telephone Number (via LINKS)	Disabled
OFF <input type="checkbox"/>	5-8	For Future Use	

[363] Partition 1 Tamper and Restorals (Section 5.3 "Communicator – Dialing")

Default	Option	ON	OFF
ON <input type="checkbox"/>	1	1st Telephone Number	Disabled
OFF <input type="checkbox"/>	2	2nd Telephone Number	Disabled
OFF <input type="checkbox"/>	3	1st Telephone Number (via LINKS)	Disabled
OFF <input type="checkbox"/>	4	2nd Telephone Number (via LINKS)	Disabled
OFF <input type="checkbox"/>	5-8	For Future Use	

[364] Partition 2 Tamper and Restorals (Section 5.3 "Communicator – Dialing")

Default	Option	ON	OFF
ON <input type="checkbox"/>	1	1st Telephone Number	Disabled
OFF <input type="checkbox"/>	2	2nd Telephone Number	Disabled
OFF <input type="checkbox"/>	3	1st Telephone Number (via LINKS)	Disabled
OFF <input type="checkbox"/>	4	2nd Telephone Number (via LINKS)	Disabled
OFF <input type="checkbox"/>	5-8	For Future Use	

[365] Partition 1 Openings and Closings (Section 5.3 "Communicator – Dialing")

Default	Option	ON	OFF
ON <input type="checkbox"/>	1	1st Telephone Number	Disabled
OFF <input type="checkbox"/>	2	2nd Telephone Number	Disabled
OFF <input type="checkbox"/>	3	1st Telephone Number (via LINKS)	Disabled
OFF <input type="checkbox"/>	4	2nd Telephone Number (via LINKS)	Disabled
OFF <input type="checkbox"/>	5-8	For Future Use	

[366] Partition 2 Openings and Closings (Section 5.3 "Communicator – Dialing")

Default	Option	ON	OFF
ON	<input type="checkbox"/>	1 1st Telephone Number	Disabled
OFF	<input type="checkbox"/>	2 2nd Telephone Number	Disabled
OFF	<input type="checkbox"/>	3 1st Telephone Number (via LINKS)	Disabled
OFF	<input type="checkbox"/>	4 2nd Telephone Number (via LINKS)	Disabled
OFF	<input type="checkbox"/>	5-8 For Future Use	

[367] System Maintenance Alarms and Restores (Section 5.3 "Communicator – Dialing")

Default	Option	ON	OFF
ON	<input type="checkbox"/>	1 1st Telephone Number	Disabled
OFF	<input type="checkbox"/>	2 2nd Telephone Number	Disabled
OFF	<input type="checkbox"/>	3 1st Telephone Number (via LINKS)	Disabled
OFF	<input type="checkbox"/>	4 2nd Telephone Number (via LINKS)	Disabled
OFF	<input type="checkbox"/>	5-8 For Future Use	

[368] System Test Transmissions (Section 5.3 "Communicator – Dialing")

Default	Option	ON	OFF
ON	<input type="checkbox"/>	1 1st Telephone Number	Disabled
OFF	<input type="checkbox"/>	2 2nd Telephone Number	Disabled
OFF	<input type="checkbox"/>	3 1st Telephone Number (via LINKS)	Disabled
OFF	<input type="checkbox"/>	4 2nd Telephone Number (via LINKS)	Disabled
OFF	<input type="checkbox"/>	5-8 For Future Use	

[370] Communication Variables

Default			Section
003	<input type="checkbox"/>	Swinger Shutdown (Alarms and Rest)	(001-014 Transmissions, 000=disabled) 5.17
003	<input type="checkbox"/>	Swinger Shutdown (Tampers and Rest)	(001-014 Transmissions, 000=disabled) 5.17
003	<input type="checkbox"/>	Swinger Shutdown (Maint and Rest)	(001-014 Transmissions, 000=disabled) 5.17
000	<input type="checkbox"/>	Communication Delay	(001-255 seconds) 5.18
030	<input type="checkbox"/>	AC Failure Communication Delay	(001-255 minutes) 3.4
003	<input type="checkbox"/>	TLM Trouble Delay	(No. of valid checks required - 000-255 x 10s) 5.11
030	<input type="checkbox"/>	Test Transmission Cycle	(001-255 days) 5.13
007	<input type="checkbox"/>	Zone Low Battery Transmission Delay	(000-255 days) 5.27

NOTE: For AC failure communications delay 000 = Disabled.

[371] Test Transmission Time of Day (Section 5.13 "Test Transmission")

Default	
9999	<input type="checkbox"/>

(Valid entries are 0000-2359, 9999 to disable)

[380] First Communicator Option Code

Default	Option	ON	OFF	Section
ON	<input type="checkbox"/>	1 Communications Enabled	Communications Disabled	5.3
OFF	<input type="checkbox"/>	2 Restorals on Bell Time-out	Restorals Follow Zones	5.7
OFF	<input type="checkbox"/>	3 Pulse Dialing	DTMF Dialing	5.3
ON	<input type="checkbox"/>	4 Switch to Pulse Dialing on 5th Attempt	DTMF Dial For All Attempts	5.3
ON	<input type="checkbox"/>	5 3rd Phone Number enabled	3rd Phone Number disabled	5.4
ON	<input type="checkbox"/>	6 Alternate Dial (1st and 3rd)	Call 1st Number, Backup to 3rd	5.4
OFF	<input type="checkbox"/>	7 Call LINKS as well as Land Line	LINKS is Backup of Land Line(s)	5.26
OFF	<input type="checkbox"/>	8 For Future Use		

[381] Second Communicator Option Code

Default	Option	ON	OFF	Section
OFF	<input type="checkbox"/>	1	Open After Alarm Kypd Ringback enabled	Open After Alarm Kypd Ringback disabled 5.20
OFF	<input type="checkbox"/>	2	Open After Alarm Bell Ringback enabled	Open After Alarm Bell Ringback disabled 5.20
OFF	<input type="checkbox"/>	3	SIA Sends Programmed Rep. Codes	SIA Sends Automatic Rep. Codes 5.6
OFF	<input type="checkbox"/>	4	Closing Confirmation Enabled	Closing Confirmation Disabled 5.20
OFF	<input type="checkbox"/>	5-8	For Future Use	

[390] LINKS Preamble (First Telephone Number) (Section 5.26 "LINKS1000 Cellular Communicator")

Default

FFFF (Program all unused digits with Hex F)

[391] LINKS Preamble (Second Telephone Number) (Section 5.26 "LINKS1000 Cellular Communicator")

Default

FFFF (Program all unused digits with Hex F)

[392] LINKS Preamble (Third Telephone Number) (Section 5.26 "LINKS1000 Cellular Communicator")

Default

FFFF (Program all unused digits with Hex F)

Downloading Programming

[401] First Downloading Option Code (Section 5.8 "Downloading")

Default	Option	ON	OFF
OFF	<input type="checkbox"/>	1	Downloading Answer enabled Downloading Answer disabled
ON	<input type="checkbox"/>	2	User Can Enable DLS Window User Can Not Enable DLS Window
OFF	<input type="checkbox"/>	3	Call-Back Enabled Call-Back Disabled
OFF	<input type="checkbox"/>	4-8	For Future Use

[402] Downloading Computer's Telephone Number (32 Digits) (Section 5.8 "Downloading")

[403] Downloading Access Code (Section 5.8 "Downloading")

Default: 5010

[404] Panel Identification Code (Section 5.8 "Downloading")

Default: 5010

[405] Answering Machine Double-call Timer (Section 5.8 "Downloading")

Default: 060 (Valid entries are 001-255)

[490] LINKS Preamble (Downloading Telephone Number) (Section 5.8 "Downloading")

Default: FFFF (Program all unused digits with Hex F)

International Programming

[701] First International Options Code (Section 5.34 "International Programming")

Default	Option	ON	OFF
ON <input type="checkbox"/>	1	50 Hz AC	60 Hz AC
OFF <input type="checkbox"/>	2	Time Base is Internal Crystal	Time Base is AC Line
OFF <input type="checkbox"/>	3	AC/DC Arming Inhibit enabled	AC/DC Arming Inhibit disabled
OFF <input type="checkbox"/>	4	All System Tamper Require Installer Reset	All System Tamper follow Restore
OFF <input type="checkbox"/>	5	6-Digit User Access Codes	4-Digit User Access Codes
OFF <input type="checkbox"/>	6-8	For Future Use	

[702] Second International Options Code (Section 5.34 "International Programming")

Default	Option	ON	OFF
ON <input type="checkbox"/>	1	For Future Use	
OFF <input type="checkbox"/>	2	Force Dialing enabled	Force Dialing disabled
OFF <input type="checkbox"/>	3	Hourly Test Transmission	Test Transmission Follows Interval
OFF <input type="checkbox"/>	4	For Future Use	
OFF <input type="checkbox"/>	5	ID Tone enabled	ID Tone disabled
OFF <input type="checkbox"/>	6	2100 HZ ID Tone	1300 Hz ID Tone
OFF <input type="checkbox"/>	7	One Time 1-Hr User enabled DLS Window	Full 6-Hr User enabled DLS Window
OFF <input type="checkbox"/>	8	Bell on FTC when armed	FTC Trouble only when armed

[703] Delay Between Dialing Attempts (Section 5.34 "International Programming")

Default	
000 <input type="text"/>	(Valid entries are 000-255 Seconds)

Module Programming

[801] RS232 Module (PC5400) Programming (Section 5.29 "On-Site Printer")

[01] Printer Configuration

Default		Option	ON	OFF
OFF	<input type="checkbox"/>	1	Printer Enabled	Printer Disabled
ON	<input type="checkbox"/>	2	Handshake from Printer (DTR)	No Handshake
OFF	<input type="checkbox"/>	3	80 Column Printer	40 Column Printer
OFF	<input type="checkbox"/>	4	300 Baud enabled	300 Baud disabled
OFF	<input type="checkbox"/>	5	1200 Baud enabled	1200 Baud disabled
ON	<input type="checkbox"/>	6	2400 Baud enabled	2400 Baud disabled
OFF	<input type="checkbox"/>	7	4800 Baud enabled	4800 Baud disabled
OFF	<input type="checkbox"/>	8	For Future Use	

[05] Printer Language Selection

Default: 01 (01=English, 02=French, 03=Spanish)

[804] PC5132 Wireless Expansion Programming (Section 5.27 "Wireless Expansion")

NOTE: For version 1.0 only. For later versions, please refer to PC5132 Installation Manual.

[01] Zone 1 Serial Number

Default
00000

5 digit Decimal entry is required

1st digit represents Transmitter Type (0,1,5-9 are not valid)

2 = UTX 3 = PIR 4 = SMOKE

Next 4 digits represent the serial number (Valid entries are 0001 to 4094)

[02] Zone 2	<input type="checkbox"/>	[18] Zone 18	<input type="checkbox"/>
[03] Zone 3	<input type="checkbox"/>	[19] Zone 19	<input type="checkbox"/>
[04] Zone 4	<input type="checkbox"/>	[20] Zone 20	<input type="checkbox"/>
[05] Zone 5	<input type="checkbox"/>	[21] Zone 21	<input type="checkbox"/>
[06] Zone 6	<input type="checkbox"/>	[22] Zone 22	<input type="checkbox"/>
[07] Zone 7	<input type="checkbox"/>	[23] Zone 23	<input type="checkbox"/>
[08] Zone 8	<input type="checkbox"/>	[24] Zone 24	<input type="checkbox"/>
[09] Zone 9	<input type="checkbox"/>	[25] Zone 25	<input type="checkbox"/>
[10] Zone 10	<input type="checkbox"/>	[26] Zone 26	<input type="checkbox"/>
[11] Zone 11	<input type="checkbox"/>	[27] Zone 27	<input type="checkbox"/>
[12] Zone 12	<input type="checkbox"/>	[28] Zone 28	<input type="checkbox"/>
[13] Zone 13	<input type="checkbox"/>	[29] Zone 29	<input type="checkbox"/>
[14] Zone 14	<input type="checkbox"/>	[30] Zone 30	<input type="checkbox"/>
[15] Zone 15	<input type="checkbox"/>	[31] Zone 31	<input type="checkbox"/>
[16] Zone 16	<input type="checkbox"/>	[32] Zone 32	<input type="checkbox"/>
[17] Zone 17	<input type="checkbox"/>		

[80] Wireless Supervisory Window

Default: 03 RF Transmitter Supervisory Window (hours), Valid entries are 01-12

NOTE: Panic Transmitters are NOT supported by PC5132 version 1.0.

Special Installer Functions

[901] Installer Walk Test Mode Enable / Disable (Section 5.33 "Walk Test [Installer]")

[902] Module Supervision Reset (Section 2.7 "Enable Supervision")

[903] Module Supervision Field (Section 2.7 "Enable Supervision")

[904] Wireless Module Placement Test (Section 5.27 "Wireless Expansion")

- Select the module / transmitter (Zones 01-32).
- Press [#] to Cancel.

Placement	Led Keypad	LCD Keypad	Bell / Buzzer
Good	Light 1 ON Steady	GOOD	1 Beep / Squawk
Fair	Light 2 ON Steady	FAIR	2 Beeps / Squawks
Bad	Light 3 ON Steady	BAD	3 Beeps / Squawks

[990] Installer Lockout Enable (Section 5.32 "Installer Lockout")

[991] Installer Lockout Disable (Section 5.32 "Installer Lockout")

[995] Restore Escort5580 Factory Default Programming (Section 5.31 "Default [Factory]")

[996] Restore PC5132 Factory Default Programming (Section 5.31 "Default [Factory]")

[997] Restore PC5400 Factory Default Programming (Section 5.31 "Default [Factory]")

[998] Restore PC5928 Factory Default Programming (Section 5.31 "Default [Factory]")

[999] Restore Factory Default Programming (Section 5.31 "Default [Factory]")

Programming LCD5500 Keypads

How to Program the LCD Keypad

If you have an LCD5500 Keypad additional programming is required for proper operation. The following is a description of the programming options available:

How to Enter LCD Programming

Step 1 - Press [★], [8], [Installer Code] (Enter Installer Programming). Press the [★] key

Step 2 - Enter the 2 digit Section number to program.

Follow the programming procedure as outlined in Section 4 - "How To Program" - in the PC5010 Installation Manual.

Programmable Labels

LCD display labels can be changed from their default settings to make operation of the system easier for the end user. The labels can be programmed via programming on a keypad or downloading (DLS-1). If done via DLS-1, please note that only a LCD keypad programmed in slot 8 will be affected. The following is the procedure for changing labels at the keypad:

Step 1 - Enter LCD Programming.

Step 2 - Enter the Number corresponding to the label you wish to program.

Step 3 - Use the arrow keys (<>) to move the underline bar underneath the letter to be changed.

Step 4 - Press the number key [1] to [9] corresponding to the letter you require. The first time you press the number the first letter will appear. Pressing the number key again will display the next letter. Refer to the following chart:

[1] - A, B, C, 1	[3] - G, H, I, 3	[5] - M, N, O, 5	[7] - S, T, U, 7	[9] - Y, Z, 9,0
[2] - D, E, F, 2	[4] - J, K, L, 4	[6] - P, Q, R, 6	[8] - V, W, X, 8	[0] - Space

Step 5 - When the required letter or number is displayed use the arrow keys (<>) to scroll to the next letter.

Step 6 - When you are finished programming the label, press the [★] key and scroll to "Save" then press the [★] key again.

Step 7 - Continue from Step 2 until all labels are programmed.

LCD5500 Programming Sections

[01] to [32] Zone Labels (14 Characters)

Default

Default

[33] Fire Alarm Label (14 Characters)

Default

[34] and [35] Partition Labels (14 Characters)

Default

Default

[40] and [41] Partition 1 and 2 "Utility Output" Label (14 Characters)

Default

[44] and [45] Partition 1 and 2 "Sensor Reset" Label (14 Characters)

Default

[51] Fail to Arm Event Message

Default

[52] Alarm When Armed Event Message

Default

[60] First User Display Mask

Default	Option	ON	OFF
ON	<input type="checkbox"/>	1 Hold Panic Keys prompt ON	Hold Panic Keys prompt OFF
ON	<input type="checkbox"/>	2 Zone Bypassing prompt ON	Zone Bypass prompt OFF
ON	<input type="checkbox"/>	3 Troubles prompt ON	Troubles prompt OFF
ON	<input type="checkbox"/>	4 Alarm Memory prompt ON	Alarm Memory prompt OFF
ON	<input type="checkbox"/>	5 Door Chime Control prompt ON	Door Chime Control prompt OFF
ON	<input type="checkbox"/>	6 Access Codes prompt ON	Access Codes prompt OFF
ON	<input type="checkbox"/>	7 User Functions prompt ON	User Functions prompt OFF
ON	<input type="checkbox"/>	8 Output Control prompt ON	Output Control prompt OFF

[61] Second User Display Mask

Default	Option	ON	OFF
OFF <input type="checkbox"/>	1	Installer Programming prompt ON	Installer Programming prompt OFF
ON <input type="checkbox"/>	2	Stay Arm prompt ON	Stay Arm prompt OFF
ON <input type="checkbox"/>	3	Quick Arm prompt ON	Quick Arm prompt OFF
ON <input type="checkbox"/>	4	Interior Arm prompt ON	Interior Arm prompt OFF
OFF <input type="checkbox"/>	5	Quick Exit prompt ON	Quick Exit prompt OFF
ON <input type="checkbox"/>	6	View Event Buffer prompt ON	View Event Buffer prompt OFF
OFF <input type="checkbox"/>	7	For Future Use	
OFF <input type="checkbox"/>	8	Enable Background Music prompt ON	Enable Background Music prompt OFF

[62] Third User Display Mask

Default	Option	ON	OFF
ON <input type="checkbox"/>	1	System Test prompt ON	System Test prompt OFF
ON <input type="checkbox"/>	2	Time and Date prompt ON	Time and Date prompt OFF
ON <input type="checkbox"/>	3	Auto-Arm Control prompt ON	Auto-Arm Days prompt OFF
ON <input type="checkbox"/>	4	Auto-Arm Time prompt ON	Auto-Arm Time prompt OFF
ON <input type="checkbox"/>	5	Download Enable prompt ON	Download Enable prompt OFF
ON <input type="checkbox"/>	6	Bright Control prompt ON	Bright Control prompt OFF
ON <input type="checkbox"/>	7	Contrast Control prompt ON	Contrast Control prompt OFF
ON <input type="checkbox"/>	8	Buzzer Control prompt ON	Buzzer Control prompt OFF

[63] Downloaded LCD Message Duration

Default: 003 (Valid entries are 000-255, 000=Unlimited Message Display. This number represents the number of times the Downloaded message is cleared by pressing any key while the message is up after timeout)

[64] Key Options

Default	Option	ON	OFF
ON <input type="checkbox"/>	1	Fire Keys enabled	Fire Keys disabled
ON <input type="checkbox"/>	2	Auxiliary Keys enabled	Auxiliary Keys disabled
ON <input type="checkbox"/>	3	Panic Keys enabled	Panic Keys disabled
OFF <input type="checkbox"/>	4-8	For Future Use	

[66] Keypad Options

Default	Option	ON	OFF
ON <input type="checkbox"/>	1	Display Access Code when Programming	Display 'X' when Programming
ON <input type="checkbox"/>	2	Local Clock Display Enabled	Local Clock Display Disabled
OFF <input type="checkbox"/>	3-8	For Future Use	

[98] Initiate Global Label Broadcast

All LCD programming is done by keypad. If more than one LCD keypad is present it is not necessary to program each independently. Labels programmed in one keypad can be broadcast to all other LCD keypads. The following is the procedure for broadcasting labels:

Step 1 - Program one LCD keypad completely.

Step 2 - Make sure all LCD keypads are connected to the Keybus.

Step 3 - Enter LCD Programming at the keypad that was programmed.

Step 4 - Enter Section [98] at the keypad that was programmed.

The keypad will now broadcast all the information programmed to all the other LCD keypads on the system.

When the keypad is finished press the [#] key to exit.

[99] Factory Default LCD Keypad

The following is the procedure for factory defaulting an LCD keypad:

- Enter LCD Programming at the keypad to be defaulted. Enter Section [99]. Press the [#] when programming is complete

ASCII Characters

032	0	a	P	`	Ɔ		—	9	Ξ	α	ρ
	048	064	080	096	112	160	176	192	208	224	240
!	1	A	Q	a	Ɔ	◻	Ɔ	†	◄	ä	q
033	049	065	081	097	113	161	177	193	209	225	241
"	2	B	R	b	Ɔ	Ɔ	Ɔ	Ɔ	×	Ɔ	θ
034	050	066	082	098	114	162	178	194	210	226	242
#	3	C	S	c	s	∟	∩	†	Ɔ	ε	◻
035	051	067	083	099	115	163	179	195	211	227	243
\$	4	D	T	d	t	`	I	†	†	∩	◻
036	052	068	084	100	116	164	180	196	212	228	244
%	5	E	U	e	u	◻	†	†	I	◻	ü
037	053	069	085	101	117	165	181	197	213	229	245
&	6	F	V	f	v	∩	加	ニ	ヨ	ρ	Σ
038	054	070	086	102	118	166	182	198	214	230	246
'	7	G	W	g	w	Ɔ	†	×	∩	g	π
039	055	071	087	103	119	167	183	199	215	231	247
(8	H	X	h	x	Ɔ	∩	†	∩	Ɔ	×
040	056	072	088	104	120	168	184	200	216	232	248
)	9	I	V	i	v	∩	†	∩	∩	∩	∩
041	057	073	089	105	121	169	185	201	217	233	249
*	:	J	Z	j	z	∩	∩	∩	∩	j	†
042	058	074	090	106	122	170	186	202	218	234	250
+	;	K	[k	∩	∩	†	†	∩	∩	∩
043	059	075	091	107	123	171	187	203	219	235	251
,	<	L	∩	l	∩	∩	∩	∩	∩	∩	∩
044	060	076	092	108	124	172	188	204	220	236	252
—	=	M	∩	m	∩	∩	∩	∩	∩	∩	∩
045	061	077	093	109	125	173	189	205	221	237	253
.	>	N	∩	n	∩	∩	∩	∩	∩	∩	∩
046	062	078	094	110	126	174	190	206	222	238	254
/	?	O	_	o	∩	∩	∩	∩	∩	∩	∩
047	063	079	095	111	127	175	191	207	223	239	255



©1997 Digital Security Controls Ltd.
1645 Flint Road, Downsview, Ontario, Canada M3J 2J6
Tel. (416) 665-8460 • Fax (416) 665-7498
Printed in Canada 29002457 R1

Programming Worksheets

DSCTM
Power 832TM
S E C U R I T Y S Y S T E M

PC5010
Version 1.1A

Table of Contents

For the Record	1	[336] Tamper Restoral Reporting Codes, Zones 17-24	14
Zone Assignment	2	[337] Tamper Restoral Reporting Codes, Zones 25-32	14
PC5010 – Zone 1-16 Assignment	2	[338] Miscellaneous Tamper Reporting Codes	14
PC5010 – Zone 17-32 Assignment	3	[339] Closing (Arming) Reporting Codes, Access Codes 1-8	15
Keypad Programming	4	[340] Closing (Arming) Reporting Codes, Access Codes 9-16	15
[000] Keypad Assignment	4	[341] Closing (Arming) Reporting Codes, Access Codes 17-24	15
Basic System Programming	5	[342] Closing (Arming) Reporting Codes, Access Codes 25-32	15
Zone Definitions	5	[343] Miscellaneous Closing (Arming) Reporting Codes	15
[001] Zone 1-8 Definitions	5	[344] Opening (Disarming) Reporting Codes, Access Codes 1-8	15
[002] Zone 9-16 Definitions	5	[345] Opening (Disarming) Reporting Codes, Access Codes 9-16	15
[003] Zone 17-24 Definitions	5	[346] Opening (Disarming) Reporting Codes, Access Codes 17-24	16
[004] Zone 25-32 Definitions	5	[347] Opening (Disarming) Reporting Codes, Access Codes 25-32	16
[005] System Times	5	[348] Miscellaneous Opening (Disarming) Reporting Codes	16
[006] Installer's Code	6	[349] Maintenance Alarm Reporting Codes	16
[007] Master Code	6	[350] Maintenance Restoral Reporting Codes	16
[008] Maintenance Code	6	[351] Miscellaneous Maintenance Reporting Codes	16
Programmable Output Options	6	[352] Test Transmission Reporting Codes	16
[009] PC5010 PGM Output Programming (PGM 1 & 2)	6	[353] Wireless Maintenance Reporting Codes	17
[010] PC5208 PGM Output Programming (PGM 3-10)	6	[360] Communicator Format Options	17
[011] PC5204 PGM Output Programming (PGM 11-14)	6	[361] Partition 1 Alarms and Restorals	17
[012] Keypad Lockout Options	6	[362] Partition 2 Alarms and Restorals	17
[013] First System Option Code	7	[363] Partition 1 Tamper and Restorals	17
[014] Second System Option Code	7	[364] Partition 2 Tamper and Restorals	17
[015] Third System Option Code	7	[365] Partition 1 Openings and Closings	17
[016] Fourth System Option Code	7	[366] Partition 2 Openings and Closings	18
Advanced System Programming	8	[367] System Maintenance Alarms and Restores	18
Zone Attribute Defaults	8	[368] System Test Transmissions	18
Zone 1-32 Attributes	8	[370] Communication Variables	18
PGM Attributes	9	[371] Test Transmission Time of Day	18
[160] Maximum Dialing Attempts to Each Phone Number	9	[380] First Communicator Option Code	18
[161] Post Dial Wait for Handshake (All Formats)	9	[381] Second Communicator Option Code	19
[162] No Activity Arming (Partition 1)	9	[390] LINKS Preamble (First Telephone Number)	19
[163] No Activity Arming (Partition 2)	9	[391] LINKS Preamble (Second Telephone Number)	19
Zone Programming	10	[392] LINKS Preamble (Third Telephone Number)	19
[201] First Partition Option Code	10	Downloading Programming	19
[202] Partition 1 Zone Assignments (1-8)	10	[401] First Downloading Option Code	19
[203] Partition 1 Zone Assignments (9-16)	10	[402] Downloading Computer's Telephone Number (32 Digits)	19
[204] Partition 1 Zone Assignments (17-24)	10	[403] Downloading Access Code	19
[205] Partition 1 Zone Assignments (25-32)	10	[404] Panel Identification Code	19
[206] Partition 2 Zone Assignments (1-8)	11	[405] Answering Machine Double-call Timer	19
[207] Partition 2 Zone Assignments (9-16)	11	[490] LINKS Preamble (Downloading Telephone Number)	19
[208] Partition 2 Zone Assignments (17-24)	11	International Programming	20
[209] Partition 2 Zone Assignments (25-32)	11	[701] First International Options Code	20
Communicator Programming	12	[702] Second International Options Code	20
[301] First Telephone Number (32 Digits)	12	[703] Delay Between Dialing Attempts	20
[302] Second Telephone Number (32 Digits)	12	Module Programming	21
[303] Third Telephone Number (32 Digits)	12	[801] RS232 Module (PC5400) Programming	21
[310] Partition 1 Identifier Code	12	[804] PC5132 Wireless Expansion Programming	21
[311] Partition 2 Identifier Code	12	Special Installer Functions	22
[320] Alarm Reporting Codes, Zones 1-8	12	[901] Installer Walk Test Mode Enable / Disable	22
[321] Alarm Reporting Codes, Zones 9-16	12	[902] Module Supervision Reset	22
[322] Alarm Reporting Codes, Zones 17-24	12	[903] Module Supervision Field	22
[323] Alarm Reporting Codes, Zones 25-32	12	[904] Wireless Module Placement Test	22
[324] Alarm Restoral Reporting Codes, Zones 1-8	12	[990] Installer Lockout Enable	22
[325] Alarm Restoral Reporting Codes, Zones 9-16	13	[991] Installer Lockout Disable	22
[326] Alarm Restoral Reporting Codes, Zones 17-24	13	[995] Restore Escort5580 Factory Default Programming	22
[327] Alarm Restoral Reporting Codes, Zones 25-32	13	[996] Restore PC5132 Factory Default Programming	22
[328] Miscellaneous Alarm Reporting Codes	13	[997] Restore PC5400 Factory Default Programming	22
[329] Priority Alarm and Restoral	13	[998] Restore PC5928 Factory Default Programming	22
[330] Tamper Reporting Codes, Zones 1-8	13	[999] Restore Factory Default Programming	22
[331] Tamper Reporting Codes, Zones 9-16	13	Programming LCD5500 Keypads	23
[332] Tamper Reporting Codes, Zones 17-24	14	How to Program the LCD Keypad	23
[333] Tamper Reporting Codes, Zones 25-32	14	LCD5500 Programming Sections	23
[334] Tamper Restoral Reporting Codes, Zones 1-8	14	ASCII Characters	Inside Back Cover
[335] Tamper Restoral Reporting Codes, Zones 9-16	14		