

ADT
Unimode 200
Technical Addendum

Document 50242 Rev A 3/7/95 ECN 95-094

Password Clear Function:

The Password Clear Function provides a means to clear programmed passwords in the event that the passwords are forgotten. The Password Clear Function offers an option to return Level 1 and Level 2 passwords back to the original factory settings. It is not necessary to contact ADT to clear programmed passwords and restore original factory settings. Use the following procedure to restore the original factory password.

With no active alarms, troubles or supervisory conditions present, press the ENTER key to access the programming mode. The following screen will appear:

1=PROGRAMMING
2=RD STATUS 3=AC/BAT

Pressing '1' will cause the following screen to appear.

KEY PASSWORD, ENTER

To clear *both Level 1 and Level 2* passwords, press **'**123'** followed by the **ENTER** key. The screen shown above will continue to be displayed, however, both passwords will have been restored to the original factory settings of **'00000'** for Level 1 and **'11111'** for Level 2.

To clear only the Level 2 password, press **'##123'** followed by the **ENTER** key. The Level 2 password will have been restored to the original factory setting of **'11111'**.