

PROGRAMMING RECORD SHEET FOR MAGNUM ALERT-825

FEATURE	
REPORT ON ALARM	
CONTROL-CENTER RESTORAL*	
ZONE RESTORAL*	
DAY ZONE	
PRIORITY WITH BYPASS**	
PRIORITY	
REMOVE AUTO-SHUNT**	
SELECTIVE SHUNT	
GROUP SHUNT	
24-HOUR PROTECTION	
AUTO-RESET	
EXIT/ENTRY ZONE	
EXIT/ENTRY FOLLOWER	
ABORT DELAY	
TIMED ALARM OUTPUT	
PULSING ALARM OUTPUT	
TIMED AUXILIARY OUTPUT	
MINI-SOUNDER ON ALARM	
7ms LOOP RESPONSE	
50ms LOOP RESPONSE	
TOUCH-TONE(R) DIALING	130
	1
TOUCH-TONE(R) ROTARY	130
BACKUP	2
BACKUP REPORTING	130
	4
DOUBLE REPORTING	130
	8
SPLIT REPORTING	131
	1
OPENING REPORT AFTER	131
ALARM	2
CONDITIONAL CLOSING	131
REPORT	4
CONDITIONAL CLOSING/ STATUS REPORT	131
	8
INSTANT/DELAY SWITCH	132
(HOME/AWAY)	1
AUTO-RESET AFTER ALARM	132
TIME-OUT	2
ZONE 6 "FIRE"	132
WITH BESK	4

ZONE							LOW
1	2	3	4	5	6	BAT	
120	120	120	120	121	121	121	
1	2	4	8	1	2	4	
122	122	122	122	123	123	123	
1	2	4	8	1	2	4	
140	140	140	140	141	141	141	
1	2	4	8	1	2	4	
142	142	142	142	143	143	143	
1	2	4	8	1	2	4	
144	144	144	144	145	145	145	
1	2	4	8	1	2	4	
146	146	146	146	147	147	147	
1	2	4	8	1	2	4	
148	148	148	148	149	149	149	
1	2	4	8	1	2	4	
150	150	150	150	151	151		
1	2	4	8	1	2		
152	152	152	152	153	153	153	
1	2	4	8	1	2	4	
154	154	154	154	155	155	155	
1	2	4	8	1	2	4	
156	156	156	156	157	157		
1	2	4	8	1	2		
158	158	158	158	159	159		
1	2	4	8	1	2		
160	160	160	160	161	161		
1	2	4	8	1	2		
162	162	162	162	163	163		
1	2	4	8	1	2		
164	164	164	164	165	165	165	
1	2	4	8	1	2	4	
166	166	166	166	167	167	167	
1	2	4	8	1	2	4	
168	168	168	168	169	169	169	
1	2	4	8	1	2	4	
170	170	170	170	171	171	171	
1	2	4	8	1	2	4	
172	172	172	172	173	173		
1	2	4	8	1	2		
174	174	174	174	175	175		
1	2	4	8	1	2		

CUSTOMER:
ADDRESS:
DATE:

EXIT	ENTRY			
178	179	180	181	DELAY TIME (seconds)

176	177	ABORT DELAY (seconds)
182	183	TIME-OUT (minutes)

169	184	185	TIME-OUT (minutes)
8			

RELAY CLOSURE ON ARMING

192	193	DOOR-CHIME TIME (1/4 seconds)

Example: For 2 seconds, enter "8" in loc. 192 (Refer to Time Selection in GLOSSARY)

TIME	1st BOX	2nd BOX
5	5	NONE
15	F	NONE
30	E	1
45	d	2
60	C	3

PROGRAMMING NOTES

\*When programming ZONE RESTORAL, CONTROL-CENTER RESTORAL must also be programmed.

\*\*When programming PRIORITY WITH BYPASS, do not program REMOVE AUTO SHUNT.



**PROGRAMMING RECORD SHEET FOR MAGNUM ALERT-825**  
Communicator Transmission Information

		ZONE						
		1	2	3	4	5	6	7
ALARM CODES	Single Digit	000	002	004	006	008	010	012
	Extended or Two Digit	001	003	005	007	009	011	013
RESTORE CODES	Single Digit	024	026	028	030	032	034	036
	Extended or Two Digit	025	027	029	031	033	035	037

OPENING/CLOSING CODES		Closing	Conditional Closing	Opening
Single Digit		User 1 2 3 4 014 016 018 020	022	User 1 2 3 4 036 040 042 044
Extended or Two Digit		015 017 019 021	** 023	039 041 043 045
Select User(s) Closing		124 124 124 124 1 2 4 8	Select User(s) Opening	126 126 126 126 1 2 4 8

KEYPAD CODES	Ambush	186 187	Fallback	188 189 190 191
--------------	--------	---------	----------	-----------------

SUBSCRIBER I.D. NUMBERS		Alarm/Restoral ID	Opening/Closing ID
Telephone 1		060 061 062 063	064 065 066 067
Telephone 2		088 089 090 091	092 093 094 095

		Format Rcvr Data	Pre-Dial Delay	Access Number	Dial-Tone Detection	Telephone Number								
Telephone 1		068 069	070	071	072	073 074 075 076 077 078 079 080	081 082 083 084 085 086 087	091 092 093 094 095 096 097	101 102 103 104 105 106 107 108	109 110 111 112 113 114 115				
Telephone 2		096 097	098	099	100									

ENTRY	RECEIVER FORMAT
Blank	ADEMCO, SILENT KNIGHT "SLOW"
1	SESCOA, VERTEX, DCI, FRANKLIN*
2	RADIONICS "FAST"*
3	SILENT KNIGHT "FAST"
4	RADIONICS, DCI, FRANKLIN "SLOW"*
5	(RESERVED)
6	(RESERVED)
7	RADIONICS BFSK*
8	ADD FOR 2300Hz HANDSHAKE

ENTRY	DATA FORMAT
Blank	EXTENDED OR SINGLE DIGIT
1	SINGLE DIGIT
2	TWO DIGIT (ON 4/2)
4	SUM CHECK

\*THESE FORMATS TYPICALLY USE A 2300Hz HANDSHAKE; ADD AN "B" TO THIS ENTRY.  
\*\*TWO-DIGIT FORMAT ONLY.