

# 2000 Series

D2112 & D2212 System Chart	Household Burglary Grade A	Household Fire	Household Fire/Burglary Combined	Central Station Burglary Grade C	Police Connected Burglary	Local Burglary	Proprietary Burglary	Local Fire/Burglary Combined	Local Fire	Local Central Station Fire Combined	Local Central Station Fire/Burg. Comb'd	Central Station Fire/Burglary Grade C	Central Station Fire	Electrically Actuated Transmitter						
NFPA Standard		74	74					<b>D2112 not listed for these applications</b>												
Minimum Hours of Standby Battery	4	24 + 4 mins alarm	24 + 4 mins alarm	4	4	4	4	<p align="center"><b>KEY</b></p> <p><b>No</b> = Not acceptable for this application</p> <p><b>Req.</b> = Required for this application</p> <p><b>Opt.</b> = Optional for this application</p> <p><b>1+</b> = One more required for this applications. Consult with appropriate standard.</p> <p><b>2+</b> = Two or more required for this application. Consult the appropriate standard. D222 and D223 may also be used for the D2212.</p> <p><b>◆◆</b> = At Least one deceptor required. You can substitute other 2-wire detectors listed for use with the D2112. You could use the D262 with the D270 wire base or other manufacturers' 4-wire deceptors.</p> <p><b>◆</b> = Listed bell (siren) housing required for burglary alarm bell or siren.</p> <p><b>(Empty Box)</b> = (Empty Box) Not used for this application .</p>												
D2103 Enclosure	Included with Panel				No	No	No													
D8103 Enclosure	Optional, order D2112M (panel on D2102 mounting skirt), D1625 Transformer. Order D101 lock for D8103				No	No	No													
D8108A Enclosure					Req.	Req.	Req.													
D8109 Enclosure					No	No	No													
D126 Battery	Opt.	1	1	Opt.	Opt.	Opt.	Opt.													
D127 Reversing Relay	Opt.	No	Opt.	Opt.	Opt.	Opt.	Opt.													
D164 Telephone Cord	Required to connect panel to RJ31X Telco Block																			
D202A/D220A Keypad	1+	1+	1+	1+	1+	1+	1+													
D262 Smoke Dectector Head D261A Base		◆◆	◆◆																	
D431, D435 ,D438, D440, D442, D448, Indicating Device	1+	1+	1+	Opt.	◆	◆	◆													
D1240 Battery	1	No	No	1	1	1	1													
D1625 Transformer	Required for all applications																			
D8004 Transformer Enclosure	Opt.	Opt.	Opt.	Opt.	Opt.	Opt.	Opt.								◆					
D8122 Derived Channel S.T.U. ®	Optional, contact Telco for availability of derived channel service.																			
D8130 Release Module	Optional																			