









# XIV. PROGRAMMING WORKSHEETS

(Factory defaults for segments are in ***bold italics*** text and "Quick Start" locations are identified with the  symbol.)

LOC	PG	DESCRIPTION	DEFAULT	PROGRAM DATA
 0	11	PHONE 1	<b><i>14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14</i></b>	-----
 1	11	PHONE 1, ACCOUNT CODE	<b><i>10 - 10 - 10 - 10 - 10 - 10</i></b>	-----
 2	11	PHONE 1, REPORTING FORMAT	<b><i>0</i></b>	--
 3	12	PHONE 1, DIAL ATTEMPTS BACKUP CONTROL	<b><i>8</i></b> <b><i>0</i></b>	-- --
4	12	PHONE 1, SELECTING EVENTS TO REPORT TO PHONE 1 Segment 1 (Circle Numbers To Program) 1 = <b><i>Alarms and Restores</i></b> 2 = <b><i>Open/Close</i></b> 3 = <b><i>Bypass</i></b> 4 = <b><i>Zone Trouble</i></b> 5 = <b><i>Power Trouble (AC Failure or Low Battery)</i></b> 6 = <b><i>Siren &amp; Telephone Fault</i></b> 7 = <b><i>Test Reports</i></b> 8 = <b><i>Program, Download, &amp; Log Full</i></b>	Segment 2 (Circle Numbers To Program) 1 = <b><i>Tampers</i></b> 2 = <b><i>Short Circuit</i></b> 3 = <b><i>Sensor Lost</i></b> 4 = <b><i>Sensor Low Battery</i></b> 5 = <b><i>Expander Trouble</i></b> 6 = <b><i>Failure To Communicate</i></b> 7 = <b><i>Zone Activity Monitor</i></b> 8 = <b><i>Reserved</i></b>	
5	12	RESERVED		
 6	12	PHONE 2	<b><i>14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14</i></b>	-----
 7	12	PHONE 2, ACCOUNT CODE	<b><i>10 - 10 - 10 - 10 - 10 - 10</i></b>	-----
 8	12	PHONE 2, REPORTING FORMAT	<b><i>0</i></b>	--
9	13	PHONE 2, DIAL ATTEMPTS BACKUP CONTROL	<b><i>8</i></b> <b><i>0</i></b>	-- --
10	13	PHONE 2, SELECTING EVENTS TO REPORT TO PHONE 2 Segment 1 (Circle Numbers To Program) 1 = Alarms and Restores 2 = Open/Close 3 = Bypass 4 = Zone Trouble 5 = Power Trouble (AC Failure or Low Battery) 6 = Siren & Telephone Fault 7 = Test Reports 8 = Program, Download, & Log Full	Segment 2 (Circle Numbers To Program) 1 = Tampers 2 = Short Circuit 3 = Sensor Lost 4 = Sensor Low Battery 5 = Expander Trouble 6 = Failure To Communicate 7 = Zone Activity Monitor 8 = Reserved	
11	13	RESERVED		
12	13	PHONE 3	<b><i>14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14</i></b>	-----
13	13	PHONE 3, ACCOUNT CODE	<b><i>10 - 10 - 10 - 10 - 10 - 10</i></b>	-----
14	13	PHONE 3, REPORTING FORMAT	<b><i>0</i></b>	--
15	13	PHONE 3, DIAL ATTEMPTS BACKUP CONTROL	<b><i>8</i></b> <b><i>0</i></b>	-- --
16	14	PHONE 3, SELECTING EVENTS TO REPORT TO PHONE 3 Segment 1 (Circle Numbers To Program) 1 = Alarms and Restores 2 = Open/Close 3 = Bypass 4 = Zone Trouble 5 = Power Trouble (AC Failure or Low Battery) 6 = Siren & Telephone Fault 7 = Test Reports 8 = Program, Download, & Log Full	Segment 2 (Circle Numbers To Program) 1 = Tampers 2 = Short Circuit 3 = Sensor Lost 4 = Sensor Low Battery 5 = Expander Trouble 6 = Failure To Communicate 7 = Zone Activity Monitor 8 = Reserved	
17	14	RESERVED		
18	14	FORMAT OVERRIDE Segment 1 (Circle Numbers To Program) 1 = ON - 1800hz transmit; OFF - 1900hz 2 = ON - 2300hz handshake; OFF - 1400hz. 3 = ON - cksum parity; OFF - double round parity 4 = ON - 2 digit event code; OFF - 1 digit code 5 = Reserved. 6 = Reserved. 7 = ON - 20 p.p.s.; OFF - 10 or 40 p.p.s. 8 = ON - 10 p.p.s.; OFF - 20 or 40 p.p.s.	Segment 2 (Circle Numbers To Program) 1 = ON - pager format (no handshake required) 2 = ON - 1400/2300 handshake 3 = Reserved 4 = Reserved 5 = ON - Contact ID 6 = ON - SIA 7 = ON - Contact ID or 4+3 8 = ON - DTMF	
		Segments 3 & 4 RESERVED		

LOC	PG	DESCRIPTION	DEFAULT	PROGRAM DATA
19	14	DOWNLOAD ACCESS CODE	<b>8-4-8-0-0-0-0-0</b>	-----
20	14	RINGS TO ANSWER DOWNLOAD	<b>8</b>	---
21	15	DOWNLOAD CONTROL Segment 1 (Circle Numbers To Program) 1 = Enables two call answering machine defeat 2 = Enables tone sniff answering machine defeat 3 = Requires callback before downloading 4 = Shutdown control panel 5 = Lock out local programming 6 = Lock out communicator programming 7 = Lock out download section 8 = Enables callback at autotest interval		
22	15	CALLBACK PHONE NUMBER	<b>14-14-14-14-14-14-14-14-14-14-14-14-14-14-14-14</b>	----- -----
23	15	FEATURE SELECTION Segment 1 (Circle Numbers To Program) 1 = Quick Arm 2 = Re-Exit 3 = <b>Auto Bypass</b> 4 = Silent Panic 5 = <b>Audible Panic</b> 6 = Auxiliary 1 7 = Auxiliary 2 8 = Multi Keypress Tamper Segment 2 (Circle Numbers To Program) 1 = LED extinguish enable 2 = Require user code for bypassing zones 3 = Bypass sounder alert 4 = <b>AC power/low battery sounder alert</b> 5 = Enables bypass toggle 6 = Enables silent auto arm 7 = Enables automatic instant 8 = Enables Instant mode toggle Segment 3 (Circle Numbers To Program) 1 = Open/Close 2 = Bypass 3 = Restore 4 = Trouble 5 = Tamper 6 = <b>Cancel</b> 7 = <b>Recent Closing</b> 8 = <b>Exit Error</b> Segment 4 (Circle Numbers To Program) 1 = Late to Close / Early to Open 2 = Auto Arm in Stay Mode 3 = Disables door delays in Night mode 4-8 = Reserved Segment 5 RESERVED		
24	16	ENTRY / EXIT TIMERS Segment 1 (Entry Time 1) Segment 2 (Exit Time 1) Segment 3 (Entry Time 2) Segment 4 (Exit Time 2) Segments 5 & 6	<b>30</b> <b>60</b> <b>30</b> <b>60</b> Reserved	
25	17	ZONES 1-8, ZONE TYPES	<b>3-5-6-6-6-6-6-6</b>	-----
29-36	17	RESERVED		
37	17	SIREN AND SYSTEM SUPERVISION Segment 1 (Circle Numbers To Program) 1 = <b>Siren sounds for telephone line cut while armed.</b> 2 = <b>Siren sounds for telephone line cut while disarmed.</b> 3 = Siren blast at arming. 4 = Siren blast at exit delay expiration. 5 = Siren blast at closing kissoff. 6 = Siren sounds during a cross-zone verification time. 7 = <b>Siren sounds for a tamper.</b> 8 = Siren blast one time for keyswitch arming, two times for disarming. ( <b>Note:</b> Must be disabled for SIA CP-01 installations.) Segment 2 (Circle Numbers To Program) 1 = Convert siren driver to voltage out. 2 = Siren sounds for expander trouble (required for U.L.). 3 = Immediate Restore by zone. 4 = Dynamic battery test performed upon arming. 5 = Battery missing test performed every 12 seconds. 6 = <b>Manual bell test performed during [*]-[4]-[4] test function.</b> 7 = Manual communicator test performed during [*]-[4]-[4] test function. 8 = Box tamper enabled.		

LOC	PG	DESCRIPTION	DEFAULT	PROGRAM DATA
37	17	Segment 3 (Circle numbers to program) 1 = Box Tamper report enabled. 2 = AC Fail report enabled. 3 = Low Battery report enabled. 4 = Auxiliary power over current report enabled. 5 = Siren supervision report enabled. 6 = Telephone Line Cut report enabled. 7 = Reserved. 8 = Expander trouble report enabled.		
		Segment 4 (Circle Numbers To Program) 1 = Failure To Communicate report enabled. 2 = Log Full report enabled. 3 = Autotest report enabled. 4 = Start and End Programming report enabled. 5 = End Download report enabled. 6 = Sensor Low Battery report enabled. 7 = Sensor Missing report enabled. 8 = First to Open / Last to Close		
		Segment 5 (Circle numbers to program) 1 = Lost Clock service LED enable. 2 = Zone Doubling enable. 3 = Disable on-board 4 zones. 4 = Enables two trips on the same cross-zone to activate the alarm. 5 = Disables bypass reports for force armed zones 6 = Reserved. 7 = Clock uses internal crystal. 8 = Disable Temporal Siren on Fire <b>(Do not disable on UL listed systems)</b>		
		Segment 6 (Circle numbers to program) 1 = Reserved. 2 = Reserved. 3 = Enable Zone Activity in Hours (not Days) 4 = Enable Daylight Savings Time (DST) 5 = Reserved 6 = Disable Clean Me report 7 = Disable Start/End Test report 8 = Reserved		
		Segment 7 - RESERVED		
38	18	SWINGER SHUTDOWN COUNT	1	-
39	18	KEYPAD SOUNDER CONTROL		
		Segment 1 (Circle numbers to program) 1 = <b>Keypad sounds for Telephone Line Cut when in the Armed state.</b> 2 = <b>Keypad sounds for Telephone Line Cut when in the Disarmed state.</b> 3 = Keypad sounds upon AC Power Failure. 4 = Keypad sounds upon Low Battery Detection. 5 = Keypad sounds during Cross Zone Trip Time. 6 = <b>Keypad sounds for Tamper Alarm.</b> 7 = Reserved. 8 = Keypad sounds for expander trouble (required for UL).		
40	19	SYSTEM TIMERS		
		Segment 1 Dynamic Battery Test duration (0-255 minutes)	0	-
		Segment 2 AC Failure report delay (0-255 minutes)	5	-
		Segment 3 Power Up Delay (0-60 seconds)	60	-
		Segment 4 Siren Time (1-254 minutes)	8	-
		Segment 5 Telephone Line Cut delay (0-255 seconds)	0	-
		Segment 6 Cross Zone Time (0-255 minutes)	5	-
		Segment 7 Chime Time in 50 mS increments (0-255)	3	-
		Segment 8 Dialer delay ( 0-255 seconds)	30	-
		Segment 9 Fire Alarm Verification Time (120-255 sec.)	0	-
		Segment 10 Listen-In Time (0-255 seconds)	0	-
		Segment 11 Zone Monitor Timer (0-255 Days)	0	-
		Segments 12 – 14 Reserved		
41	19	SPECIAL FEATURES		
		Segment 1 (Circle numbers to program) 1 = Enables 6-digit code option. All arm/disarm/Go To Program codes require six digits. 2 = Requires valid user code entry for [*]-[9]-[8] and [*]-[9]-[9] functions to work. 3 = Enable Auto Cancel / Abort. 4 = Enable Walk-Test Mode. 5 = Reserved.		

LOC	PG	DESCRIPTION	DEFAULT	PROGRAM DATA
42	19	GO TO PROGRAM CODE	<b>9-7-1-3-0-0</b>	-----
43	19	GO TO PROGRAM CODE & AUTHORIZATION Segment 1 (Circle numbers to program) 1 = Reserved. 2 = Enables "Go To Program Code" as an arm only code. 3 = Enables "Go To Program Code" as an arm only after closing. 4 = Enables "Go To Program Code" as a master arm/disarm code (can change user codes) 5 = Enables "Go To Program Code" as an arm/disarm code. 6 = Enables "Go To Program Code" to bypass zones. 7 = Enables "Go To Program Code" opening and closing reports. 8 = Reserved. Segment 2 Reserved		
44	19	DURESS CODE	<b>15-15-15-15-15-15</b>	-----
45	19	RESERVED		
46	20	AUXILIARY OUTPUTS 1-2 SPECIAL TIMING Segments (Aux Out)		1 2
		1 = Aux output timed in minutes.		1 1
		2 = Aux output to latch.		2 2
		3 = <b>Aux output to stop timing upon user code entry.</b>		<b>3 3</b>
		4 = Aux output to activate only between closing & opening time.		4 4
		5 = Aux output to activate only between opening & closing time.		5 5
		6 = Invert auxiliary output (0 Volts going to 12V when activated).		6 6
		7 = Reserved		7 7
		8 = Reserved		8 8
47	20	AUXILIARY OUTPUT #1, EVENT & TIME Segment 1: Event number for output # 1 Segment 2: Timing for output # 1	<b>0=Burglary alarm</b> <b>10 seconds</b>	
48	20	AUXILIARY OUTPUT #2, EVENT & TIME Segment 1: Event number for output # 2 Segment 2: Timing for output # 2	<b>1=Fire alarm</b> <b>10 seconds</b>	
49	20	AUXILIARY OUTPUT #3, EVENT & TIME Segment 1: Event number for output # 3 Segment 2: Timing for output # 3	<b>2= 24 Hour Alarm</b> <b>10 seconds</b>	
50	20	AUXILIARY OUTPUT #4, EVENT & TIME Segment 1: Event number for output # 4 Segment 2: Timing for output # 4	<b>21-Armed State</b> <b>0=Follow condition</b>	
51	20	AUTOTEST CONTROL Seg 1: Program a "1" if the interval is hours, a "0" if in days. Add a "2" to suppress the daily test or a "3" to suppress the hourly test. Seg 2: Program the autotest interval from 1-255 days or hours. Seg 3: Program the autotest report in 24-hour time format. Seg 4: Program the autotest report time, minutes after the hour.	<b>1</b> <b>24</b> <b>2</b> <b>0</b>	
52	21	OPENING TIME Seg 1: Hour of the opening time. Seg 2: Minutes after the hour of opening time.	<b>8</b> <b>0</b>	
53	21	CLOSING TIME / AUTO ARMING TIME Seg 1: Hour of closing time / auto arming time. Seg 2: Minutes after hour of closing / auto arming time.	<b>20</b> <b>0</b>	
54	21	DAYS OF THE WEEK SYSTEM IS OPEN Segment 1:	Sunday Monday Tuesday Wednesday Thursday Friday Saturday Reserved	
			<b>1 2 3 4 5 6 7 8</b>	
55	21	DAYS OF THE WEEK "AUTO ARMING" WILL OCCUR Segment 1:	Sunday Monday Tuesday Wednesday Thursday Friday Saturday Reserved	
			<b>1 2 3 4 5 6 7 8</b>	

**COMMUNICATOR CODES FOR SLOW SPEED FORMATS ONLY**

The digit programmed in each of the following locations will be sent as the upper HEX digit in place of the alarm event code. The zone ID or user ID will always be reported as the lower HEX digit (1-F). For example, if the zone ID or user ID is 6, the 4+2 lower digit will be "6". (Refer to Appendix 4 on page 41.)

✍ If Segments 2-8 are left as "0" (unprogrammed), they will follow the Segment 1 selection.  
 If Segment 1 is left as "0" and the feature is enabled, the NX-4V2 will report "'A".

LOC	PG	DESCRIPTION	DEFAULT	PROGRAMMING DATA
56	22	RESTORE COMMUNICATOR CODE	0	--
57	22	BYPASS COMMUNICATOR CODE	0	--
58	22	TAMPER COMMUNICATOR CODE	0	--
59	22	TROUBLE COMMUNICATOR CODE	0	--
60	22	SENSOR LOW BATTERY COMMUNICATOR CODE	0	--
61	22	SENSOR MISSING COMMUNICATOR CODE	0	--
62	22	DURESS	0-0	--
63	22	AUXILIARY 1	0-0	--
64	22	AUXILIARY 2	0-0	--
65	22	KEYPAD PANIC	0-0	--
66	22	KEYPAD MULTIPLE CODE ENTRY TAMPER	0-0	--
67	22	BOX TAMPER / BOX TAMPER RESTORE	0-0-0-0	----
68	22	AC FAIL / AC RESTORE	0-0-0-0	----
69	22	LOW BATTERY / LOW BATTERY RESTORE	0-0-0-0	----
70	22	POWER SHORT / POWER SHORT RESTORE	0-0-0-0	----
71	22	BELL TAMPER / BELL TAMPER RESTORE	0-0-0-0	----
72	22	TELEPHONE LINE CUT / LINE CUT RESTORE	0-0-0-0	----
73	22	Reserved	0-0-0-0	----
74	23	EXPANDER TROUBLE / EXP TROUBLE RESTORE	0-0-0-0	----
75	23	FAILURE TO COMMUNICATE	0-0	--
76	23	LOG FULL COMMUNICATOR CODE	0-0	--
77	23	OPENING CODE COMMUNICATOR CODE	0	--
78	23	CLOSING COMMUNICATOR CODE	0	--
79	23	AUTOTEST COMMUNICATOR CODE	0-0	--
80	23	RECENT CLOSING AND EXIT ERROR	0-0	--
81	23	START PROGRAMMING / END PROGRAMMING	0-0-0-0	----
82	23	END DOWNLOAD	0-0-0-0	XX--
83	23	CANCEL COMMUNICATOR CODE	0	--
84-109	23	RESERVED		
110	23	ZONE TYPE 1 ALARM EVENT CODE	8	--
111	23	ZONE TYPE 1 CHARACTERISTIC SELECT		
		Segment 1		
		1 = Fire (enable for fire zone)	5 = Delay 1 zone (enable to follow Timer 1 Entry/Exit times)	
		2 = 24-Hour (enable for non-fire 24 hour)	6 = Delay 2 zone (enable to follow Timer 2 Entry / Exit times)	
		3 = Keyswitch zone	7 = Interior (Enable for auto bypass or stay arming)	
		4 = Follower (enable for burg zones that are instant during non-entry times)	8 = Local Only (enable if zone is not to be reported)	
		Segment 2		
		1 = <b>Keypad audible on alarm.</b>	5 = <b>Bypassable.</b>	
		2 = <b>Yelping siren on alarm.</b>	6 = Group Shunt.	
		3 = Temporal siren on alarm.	7 = Force armable.	
		4 = Chime.	8 = Entry Guard.	
		Segment 3		
		1 = Fast Loop Response.	5 = <b>Dialer Delay zone.</b>	
		2 = Double End of Line Tamper zone.	6 = <b>Swinger zone.</b>	
		3 = <b>Trouble zone (Day zone).</b>	7 = <b>Restore reporting.</b>	
		4 = Cross Zone.	8 = <b>Listen-In.</b>	
		Segment 4		
		1 = Zone Activity Monitor.		
		2 = End of Line Resistor Defeat.		
		3-8 = Reserved.		
		Segment 5 RESERVED		

## LOCATIONS 112 – 169

**EVEN NUMBERED.....** Contains the event code sent for Contact ID or SIA and chosen from the list on pg 16. **4+2 Format Note:** If 4+2 format is being used, the number programmed in this location will be sent as the upper hex digit. The digit should be from 1 to 15 when using 4+2 formats. The zone ID or user ID will be the lower hex digit of the zone that is in alarm.

**ODD NUMBERED.....** The defaults listed below represent the five segments of each of those locations. Use the data from location 111 (table on pg 32 and instructions on pg 23)

LOC	DESCRIPTION	DEFAULT	PROGRAMMING DATA
112	ZONE TYPE 2 ALARM EVENT CODE	2	___
113	ZONE TYPE 2 CHARACTERISTIC SELECT	2-125-78-0-0	___
114	ZONE TYPE 3 ALARM EVENT CODE	7	___
115	ZONE TYPE 3 CHARACTERISTIC SELECT	5-1245-5678-0-0	___
116	ZONE TYPE 4 ALARM EVENT CODE	5	___
117	ZONE TYPE 4 CHARACTERISTIC SELECT	45-125-5678-0-0	___
118	ZONE TYPE 5 ALARM EVENT CODE	5	___
119	ZONE TYPE 5 CHARACTERISTIC SELECT	457-125-5678-0-0	___
120	ZONE TYPE 6 ALARM EVENT CODE	4	___
121	ZONE TYPE 6 CHARACTERISTIC SELECT	0-1245-5678-0-0	___
122	ZONE TYPE 7 ALARM EVENT CODE	0	___
123	ZONE TYPE 7 CHARACTERISTIC SELECT	2-0-78-0-0	___
124	ZONE TYPE 8 ALARM EVENT CODE	1	___
125	ZONE TYPE 8 CHARACTERISTIC SELECT	1-13-378-0-0	___
126	ZONE TYPE 9 ALARM EVENT CODE	7	___
127	ZONE TYPE 9 CHARACTERISTIC SELECT	6-1245-5678-0-0	___
128	ZONE TYPE 10 ALARM EVENT CODE	2	___
129	ZONE TYPE 10 CHARACTERISTIC SELECT	24-5-78-0-0	___
130	ZONE TYPE 11 ALARM EVENT CODE	3	___
131	ZONE TYPE 11 CHARACTERISTIC SELECT	3-0-0-0-0	___
132	ZONE TYPE 12 ALARM EVENT CODE	5	___
133	ZONE TYPE 12 CHARACTERISTIC SELECT	457-125-45678-0-0	___
134	ZONE TYPE 13 ALARM EVENT CODE	4	___
135	ZONE TYPE 13 CHARACTERISTIC SELECT	0-12458-5678-0-0	___
136	ZONE TYPE 14 ALARM EVENT CODE	7	___
137	ZONE TYPE 14 CHARACTERISTIC SELECT	5-12456-5678-0-0	___
138	ZONE TYPE 15 ALARM EVENT CODE	5	___
139	ZONE TYPE 15 CHARACTERISTIC SELECT	457-1256-5678-0-0	___
140	ZONE TYPE 16 ALARM EVENT CODE	4	___
141	ZONE TYPE 16 CHARACTERISTIC SELECT	0-12456-5678-0-0	___
142	ZONE TYPE 17 ALARM EVENT CODE	7	___
143	ZONE TYPE 17 CHARACTERISTIC SELECT	5-1245-25678-0-0	___
144	ZONE TYPE 18 ALARM EVENT CODE	5	___
145	ZONE TYPE 18 CHARACTERISTIC SELECT	457-125-25678-0-0	___
146	ZONE TYPE 19 ALARM EVENT CODE	4	___
147	ZONE TYPE 19 CHARACTERISTIC SELECT	0-1245-25678-0-0	___
148	ZONE TYPE 20 ALARM EVENT CODE	7	___
149	ZONE TYPE 20 CHARACTERISTIC SELECT	6-1245-25678-0-0	___
150	ZONE TYPE 21 ALARM EVENT CODE	15	___
151	ZONE TYPE 21 CHARACTERISTIC SELECT	24-15-78	___
152	ZONE TYPE 22 ALARM EVENT CODE	20	___
153	ZONE TYPE 22 CHARACTERISTIC SELECT	24-15-78	___
154	ZONE TYPE 23 ALARM EVENT CODE	21	___
155	ZONE TYPE 23 CHARACTERISTIC SELECT	24-15-78	___
156	ZONE TYPE 24 ALARM EVENT CODE	22	___
157	ZONE TYPE 24 CHARACTERISTIC SELECT	1-13-378	___
158	ZONE TYPE 25 ALARM EVENT CODE	14	___
159	ZONE TYPE 25 CHARACTERISTIC SELECT	248-45-0-0-0	___
160	ZONE TYPE 26 ALARM EVENT CODE	5	___
161	ZONE TYPE 26 CHARACTERISTIC SELECT	467-125-5678-0-0	___
162	ZONE TYPE 27 ALARM EVENT CODE	5	___
163	ZONE TYPE 27 CHARACTERISTIC SELECT	457-1257-5678-0-0	___
164	ZONE TYPE 28 ALARM EVENT CODE	7	___
165	ZONE TYPE 28 CHARACTERISTIC SELECT	6-12457-5678-0-0	___
166	ZONE TYPE 29 ALARM EVENT CODE	5	___
167	ZONE TYPE 29 CHARACTERISTIC SELECT	457-125-5678-1-0	___
168	ZONE TYPE 30 ALARM EVENT CODE	7	___

LOC	DESCRIPTION	DEFAULT	PROGRAMMING DATA						
169	ZONE TYPE 30 CHARACTERISTIC SELECT	<b>5-1245-5678-1-0</b>	-----						
170-205	RESERVED								
206	DAYS OF THE WEEK "AUTO DISARMING" WILL OCCUR								
	Segment 1	Sunday	Monday	Tuesday	Wednesday	Thursday	Friday	Saturday	Reserved
	1	2	3	4	5	6	7	8	

**ZONE WORKSHEET**

1		5	
2		6	
3		7	
4		8	

**NOTES**