

MCT-501

Advanced Acoustic Sensor / PowerCode Transmitter



Installation Instructions

1. INTRODUCTION

The MCT-501 combines two modules:

- The Sentrol Inc. ShatterPro™ acoustic sensor with Pattern Recognition Technology™ (Protected under U.S. Patent 5,192,931)
- The Visonic Ltd. MCT-302 PowerCode™ transmitter




Figure 1. General View




Figure 2. Module Identification

1.1 Acoustic Sensor

The acoustic sensor module of the MCT-501 is omni-directional, providing 360° coverage. Coverage is measured from the sensor to the point on the glass farthest from the sensor (see Fig. 3). The sensor can be mounted as close as 1 m (3.3 ft) from the glass.




Figure 3. Typical Range Measurement

When mounted on opposite wall or adjoining walls, the range is 6 m (20 ft) for plate, tempered, laminated and wired glass.

When mounted on the ceiling, the maximum range is 6 m (20 ft) for plate, tempered, laminated and wired glass

For armor-coated glass, mount the sensor no more than 3.65 m (12 ft) from the glass.

1.2 PowerCode Transmitter

The acoustic sensor shares its housing with a miniature transmitter which has a unique 24-bit PowerCode ID, selected in the factory from over 16 million possible code combinations.

Upon alarm (glass break detection), a digital message is transmitted, composed of the PowerCode ID followed by various status and message-type markers. Alarm and other data are thus forwarded to the wireless alarm control panel.

Since transmitted messages might collide with transmissions from other PowerCode transmitters used in the system, a smart anti-collision transmission sequence is used.

The MCT-501 is protected by a tamper switch that is activated when the cover is removed. In a tamper situation, a message is transmitted with the "tamper alert" marker ON.

A periodic supervision message, distinguished by a specific marker, is transmitted automatically once in 60 minutes. The wireless control panel is thus informed, at regular intervals, of the sensor's active participation in the system.

A red LED mounted on the transmitter PCB (visible only when the cover is off) lights whenever alarm or tamper events are reported. The LED does not light while a supervision message is being transmitted.

Operating power is obtained from an on-board 3.6 V Lithium Thionyl Chloride battery. A weak battery will cause a "low battery" marker to be added to any message transmitted.

2. SPECIFICATIONS

ACOUSTIC SENSOR SECTION

Microphone: Omni-directional electret

Alarm Duration: 4 seconds

RF immunity: 20 V/m, 1 MHz to 1000 MHz

Temperature range: -10° to 50°C (14° to 120°F)

Recommended Glass Size:

Minimum: 0.3 x 0.6 m (1 x 2') or larger glass thickness

Plate: 2.4 to 6.4 mm (3/32 to 1/4")

Tempered: 3.2 to 6.4 mm (1/8 to 1/4")

Wired: 6.4 mm (1/4")

Laminated: 3.2 to 6.4 mm (1/8" to 1/4")

POWERCODE TRANSMITTER SECTION

Frequency (MHz): 315, 404, 418, 433.92 or other frequencies according to local requirements.

Transmitter's ID Code: 24-bit digital word, over 16 million combinations, pulse width modulation.

Overall Message Length: 36 bits

Message Repetition: One-shot transmission (default) or once every 3 minutes.

Supervision: Signaling at 60-minute intervals (U.S. version) or 15 minute interval (UK version)

Response to Tamper Event: Tamper report every 3 minutes (until the tamper switch is restored).

POWER SUPPLY

Power Source: 3.6 V Lithium Thionyl Chloride (LiSOCl₂) battery, size 1/2 AA, Tadiran TL-5902 or equivalent.

Nominal Battery Capacity: 1.2 Ah

Current Drain: 24 µA standby, 13 mA on alarm (including LED)

Battery Life (with LED on):

@ 10 transmissions per day: Over 10 years

@ 50 transmissions per day: About 6 years

Battery Supervision: Automatic transmission of battery condition data as part of any status report.

PHYSICAL

Operating Temperature: 0°C to 49°C (32°F to 120°F).

Dimensions: 80 x 108 x 43 mm (3.13 x 4.24 x 1.70 in.).

Weight (less battery): 130 g (4.6 oz)

Housing Material and Color: Flame retardant ABS, white

Standards: Meets FCC Part 15, ETS 300-220 and MPT1349

The 418 & 433.92 MHz models of this device comply with the European Council Directive EMC 89/336/EEC & 92/31/EEC, and bear the CE mark and certification.

3. INSTALLATION

3.1 Optimizing Detection and Avoiding False Alarms

For best detection, avoid installing in:

- Rooms with lined, insulating, or sound deadening drapes.
- Rooms with closed wooden window shutters inside.

For best false alarm immunity:

- Avoid 24-hour loop applications (perimeter loop OK).
- Don't use where white noise, such as air compressor noise, is present (a blast of compressed air may cause a false alarm).
- Avoid rooms smaller than 3 x 3 m (10 x 10 ft) and rooms with multiple noise sources such as small kitchens, glass booths noisy areas, garages, small bathrooms, etc.

Areas to avoid:

- Glass airlocks and glass vestibule areas
- Noisy kitchens
- Residential car garages
- Small utility rooms
- Stairwells
- Small bathrooms
- Other small acoustically live rooms. For glass break protection in such applications, use shock sensors on the windows or window frames.

Do Not Install In Humid Rooms The Wireless MCT-501 is not hermetically sealed. Excess moisture on the circuit board can eventually cause a short and a false alarm.

Avoid 24-Hour Loop Applications The MCT-501 is recommended for perimeter loops and is designed to function in occupied area. In 24-hour loop applications, where the sensor is armed all day and all night, the false alarm prevention technology will be pushed to its limit. Some sounds can duplicate the glass break pattern the acoustic sensor detects.

Install the MCT-501 on a perimeter loop which is armed whenever the door and window contacts are armed.

Protecting Occupied Areas

The false alarm immunity is best in rooms with only moderate noise. For 24-hour occupied area protection, use shock sensors.

Proper Testing

The MCT-501 is designed to detect the breaking of framed glass mounted in an outside wall. Testing the sensor with unframed glass, broken bottles, etc., may not trip the sensor. The sensor typically does not trip to glass breaking in the middle of the room. No burglar breaks glass in the middle of a room, so such "breaks" are false alarms.

NOTE: MCT-501 may not consistently detect cracks in glass, or bullets which break through the glass. Glass-break sensors should always be backed up by interior protection.

For best false alarm immunity the sensor should be located at least 1.2 m (4 ft) away from noise sources (televisions, speakers, sinks, doors, etc.). The sensor must always be in direct line of sight of all protected windows. It cannot consistently detect glass breaking around corners, in other rooms, etc. Front or back, up or down orientation is not necessary.

3.2 Sound Travel Considerations

Since the sound of breaking glass travels directionally out from the broken window, the best location for mounting the sensor is on the opposite wall - assuming the glass to be protected is within the sensor's range and line of sight. The ceiling and adjoining (side) walls are also good sensor locations. A ceiling mounted sensor will have better detection if positioned 2 - 3 m (6 - 10 ft) away from the protected glass into the room.

As with all glass-break sensors, detection is reduced with same-wall mounting, since such detection is partially dependent on glass break sound reflecting off the opposite wall. Test the range with Sentrol 5709C unit held flat against the glass. There may be a reduction in range, depending on room acoustics.

3.3 Preparing the Unit

A. Use a screwdriver to separate the cover from the base, as shown in Figure 4.




Figure 4. Opening the Unit

B. Get to know the items indicated in Fig. 5 - they are all relevant to the steps you will have to take in the course of installation.




Figure 5. Inside View

C. Verify that all 4 DIP switch levers are set to OFF as shown in Figure 6 below. If not - set them all OFF.




Figure 6. DIP Switches - Correct Position

D. Insert the battery into the battery clips, as shown in Figures 7 and 8. **Observe Polarity!**




Figure 7. Battery Insertion

Use only Lithium Thionyl Chloride battery (Tadiran TL-5902 or equivalent).




Figure 8. Battery in Place

E. Click the tamper switch once and release it to reset the transmitter at power up.

Note: Since the cover is removed and power is applied, a tamper situation exists. Verify that the MCT-501 transmits (the transmit LED lights briefly) once every 3 minutes.




Figure 9. Resetting the Unit

3.4 ID Enrollment and Mounting

Note: It is much easier to enroll the transmitter ID while holding the MCT-501 in your hand, close to the control panel.

- A. Refer to the control panel's or PowerCode receiver's installation instructions for enrolling transmitter IDs.
- B. When required to initiate a transmission for enrolling the transmitter's ID, press the unit's tamper switch and release it.

The tamper message transmitted as a result (the transmit LED blinks) will do the job.

- C. Use the base as a template - press it against the wall at the selected mounting position and mark the drilling points through the mounting holes. Drill two holes and attach the base to the wall using the wall plugs and screws.
- D. Align the cover with the base and push it until it snaps shut.

4. TESTING PROCEDURES

4.1 How Does the Test Mode Works

The Pattern Recognition Technology™ of the MCT-501 ignores most false alarm sounds, including glass-break testers. In order to test the MCT-501, a test mode is used. With the sensor in the test mode, processing of the glass-break pattern in the upper and lower frequencies is disabled. The MCT-501 is then sensitive only to the mid-range frequencies which the Sentrol 5709C hand-held tester reproduces. It's the mid-range frequencies that determine sensor coverage.

IN THE NORMAL MODE THE DETECTION LED FLASHES BRIEFLY UPON RECEIVING A LOUD SOUND. WHEN IN THE NORMAL MODE, THE MCT-501 WILL NOT TRIP TO THE TESTER'S SIGNAL, UNLESS THE TESTER IS HELD NEXT TO THE SENSOR.

NOTE: Each time the sensor alarms it also goes into the TEST mode for one minute.

4.2 Switching the Sensor to the Test Mode

Use the Sentrol 5709C or the Intellisense FG701 hand-held tester to switch the sensor into the test mode. Set the tester to tempered glass, hold the tester speaker directly on top of the sensor and activate the tester. The sensor will alarm, then it will go into test mode for one minute. When in test mode the LED on the sensor will flash continuously. prolong the test session by firing the tester at the sensor at least once a minute.

4.3 Testing the Sensor (see Figure 10).

- A. Holding the tester near the surface of the glass, aim the tester at the MCT-501 and press the test button. If drapes or blinds are present, test with the hand-held tester behind the closed drapes or blinds (do not install the sensor where heavy or lined drapes are used). If the sensor is mounted on same wall, point the tester at the opposite wall.




Figure 10. Testing the MCT-501

- B. The tester has a different setting for each type of glass. It should always be set for tempered or laminated glass (either is correct and both have the same range) unless you are certain that all the protected glass is plate glass.
- C. When the LED on the sensor goes solid momentarily while the tester is triggered, the glass is within detection range.

- D. If the LED does not go solid, but continues flashing as before, re-position the sensor closer to the protected windows and retest. This may require adding sensors in order to achieve adequate coverage. It is very rare that the sensor will not activate within its stated range of coverage. Double check adequate battery strength in the hand-held tester. A new tester battery will likely restore the range.

Note: The sensor will automatically change from test mode to normal mode approximately one minute after the last signal received from the hand-held tester.

IMPORTANT! Room acoustics can artificially extend the range of a glass-break sensor. The specified range of the MCT-501 has been established for worst-case conditions. While the sensor is likely to function at additional range, it may miss a "minimum output" break, or room acoustics may be changed at some future time, restoring sensor coverage back to the normal range of 6 m (20 ft). Do not exceed the rated range of the sensor, regardless of what the tester shows.

4.4 Hand Clap Test

The MCT-501 can be checked by the installer or end user while in normal mode, simply by clapping hands loudly under the sensor. The LED will flash twice, but the sensor will not trip. This verifies visually that there is power to the sensor, and that the microphone and circuit board are functioning.

The hand clap activation is only momentary, so there is no appreciable effect on battery life.

INSTALLATION TIPS

- A. The MCT-501 is designed to detect the shattering of framed glass mounted in an outside wall. "Testing" the sensor with unframed glass, broken bottles, etc. may not trip the sensor. The MCT-501 typically does not trip to glass break tests in the middle of a room as such breaks are false alarms.
- B. False alarms are most likely to occur when installed on a 24-hour loop in glass airlocks and glass vestibule areas, when mounted above sinks, when used in residential car garages and in other small, acoustically live rooms and rooms where multiple sounds can reflect and eventually duplicate the glass break frequency pattern. For occupied area glass break protection in such applications, use shock sensors.
- C. Installing the MCT-501 on 24-hour loops will increase false alarms. The MCT-501 is recommended for perimeter loops and is designed to function without false alarms in occupied areas. On a 24-hour loop, which is armed all day/all night every day, the false alarm technology will be pushed to its limit since some sounds in some conditions can duplicate the points on the glass break pattern that the MCT-501 detects. Install the MCT-501 on a perimeter loop, which is armed whenever the door and window contacts are armed. For occupied area installations, MCT-501's false alarm immunity is best in rooms with only moderate noise.
- D. MCT-501 detects the shattering of glass. Like all glass-break sensors, it may not consistently detect cracks in glass, or bullets that break through the glass or break out the glass. Glass-break sensors should always be backed up by interior protection.

5. MISCELLANEOUS COMMENTS

Visonic Ltd. wireless systems are very reliable and are tested to high standards. However, due to their low transmitting power and limited range (required by FCC and other regulatory authorities), there are some limitations to be considered:

- A. Receivers may be blocked by radio signals occurring on or near their operating frequencies, regardless of the code selected.
- B. A repeater can only respond to one transmitter signal at a time.
- C. Wireless equipment should be tested regularly to determine whether there are sources of interference and to protect against faults.

This device complies with FCC Rules, Part 15. Operation is subject to two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference that may be received or that may cause undesired operation.

WARNING! Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The digital circuitry of this device has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in residential installations. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio and television reception. However, there is no guarantee that interference will not occur in a particular installation. If this device does cause such interference, which can be verified by turning the device off and on, the user is encouraged to eliminate the interference by one or more of the following measures:

- Re-orient or re-locate the receiving antenna.
- Increase the distance between the device and the receiver.
- Connect the device to an outlet on a circuit different from the one which supplies power to the receiver.
- Consult the dealer or an experienced radio/TV technician.