

# ADEMCO VISTA-10SE

An ADEMCO Group Company

control  
panel

**With the Vista-10SE, you're limited only by your desires and imagination**

**W**ith six zones and 5800 wireless zone expansion, the Vista-10SE is the industry's most economical and sophisticated control that can operate lights and appliances.

**Dependable features to meet your most demanding installations:**

- ◆ Six hardwired zones standard
- ◆ Expands to 22 total zones when using 5800 wireless, 14 zones with 5700 wireless
- ◆ Seven user codes
- ◆ Two-way downloading
- ◆ Supports up to four relays
- ◆ False alarm prevention features



***The Vista - 10SE offers a new level of flexibility with superior security features, end user simplicity and powerful control.***

**End users will appreciate the easy-to-use convenience and control features of the Vista-10SE:**

- ◆ Wireless remote control - single button control system with a wireless device: the 5804 - a four-button, programmable wireless key or the 5804BD, a bi-directional programmable wireless key with system status feedback
- ◆ Single or dual button wireless personal panic: 5802MN and 5802MN2
- ◆ Home automation to activate lights, appliances, garage doors, and numerous other devices
- ◆ Vista Interactive Phone Module (VIP) that gives the end user control of their system from any touch tone phone; the 4285 VIP module responds in clear English, with over a 100 word vocabulary
- ◆ Full English display keypads for clear understanding of system status and zone locations
- ◆ Paging - openings, closings, alarm and trouble messages can be sent directly to a pager, allowing system status to be confirmed; parents can use this feature to verify that their children have arrived home
- ◆ Quick exit that enables users to leave the house for a brief time without disarming the system



# ADEMCO VISTA-10SE

An ADEMCO Group Company

## SPECIFICATIONS:

### ELECTRICAL

- ◆ 500 mA, Aux - 12 VDC
- ◆ 16.5 VAC/25 VA transformer
- ◆ Alarm output 12 VDC, 2.0 amps max
- ◆ For UL installations, combined Aux and alarm output cannot exceed 600mA

### OUTPUT CONTROL

- ◆ Supports one relay board (part number 4204) for four relays

### ZONES

- ◆ Six hardwired zones
  - Selectable response: 10msec, 350msec, 750msec
  - Expandable to 22 zones using 5800 wireless
  - Expandable to 14 zones using 5700 wireless
  - 16 zone types to choose from
  - Programmable swinger suppression

### SUPPORTED DEVICES

#### Hardwired Expansion Devices

- ◆ 4204 supports up to four relays-15mA (each active relay draws 40mA)
- ◆ Keypads
  - 6139 custom English (required for programming) - 100mA
  - 6128 fixed English LCD - 85mA/40mA
- ◆ Voice module 4285 VIP - 160mA
- ◆ Four wire smoke detectors

### WIRELESS RECEIVER SYSTEMS

- ◆ 5800 receivers
  - 5881L up to eight zones - 50mA
  - 5881M up to 16 zones - 50mA

- ◆ 5700 receivers
  - 4281L up to four zones - 30mA
  - 4281M up to eight zones - 30mA
- ◆ All receivers support
  - Diversity reception with two antennae
  - Remote mounting for best location
  - Unique supervision and low battery indications by point

### TRANSMITTERS

- ◆ 5800 Series
  - Three volt Duracell lithium batteries
  - One mile range
  - Tamper is standard
- ◆ 5700 Series
  - Nine volt alkaline or lithium batteries
  - 3,000 foot range

### AGENCY LISTINGS

- ◆ UL Residential Fire and Burglary and CFM

### COMMUNICATIONS

- ◆ Touch tone or pulse
- ◆ Formats supported
  - ADEMCO Contact ID
  - ADEMCO 4 + 2 Express
  - ADEMCO low speed
  - Sescoa/Radionics
- ◆ 3 + 1, 4 + 1 and 4 + 2 reporting
- ◆ Reporting capabilities: Split, Dual, Split/Dual, Pager

#### Ordering Information

Part No.	Description
Vista-10SE	Control Panel