



The DMP 692 Security Command® is a highly attractive, user-friendly LED keypad with three optional 2-button Panic keys. Sixteen LEDs on the 692 include three system status LEDs, three armed status LEDs, and ten zone LEDs. The 692 also includes an easy-to-read backlit keyboard, simple COMMAND key arming, and a built-in alert buzzer. The 692 is encased in a stylish and durable plastic housing with removable base for easy installation.

692 SECURITY COMMAND® LED KEYPAD

FEATURES

- Three system LEDs for at-a-glance system status: ready, trouble, and power
- Three armed status LEDs: armed, stay, and instant
- 10 individual zone LEDs
- 2-button panic keys for panic, emergency, and fire
- No addressing required—use as many as you need
- Simple arming and disarming by entering a user code
- One key arming for perimeter or sleep modes
- Zone monitoring feature
- Connects to panel with 4-wire cable
- Four short tones inform user of unsuccessful operation
- Audible tone on each press of a key
- Audible entry delay tone
- Ambush code
- Quick key for adding, deleting, or changing user codes
- Zone LEDs indicate normal, trouble, bypassed, and alarm conditions
- Relay output control from keypad
- Change user codes from keypad
- Bypass individual zones

STATUS LEDs

The 692 provides ready, trouble, and power system status LEDs that inform users at-a-glance the current condition of their system. There are also armed, stay, and instant status LEDs that show users the current armed state of the system and can help decrease false alarms.

EASY ARMING AND DISARMING

Complete most system operations, such as arming and disarming, by simply entering a user code. An additional programming option allows the COMMAND key along with the 1, 2, and 3 keys to be used instead of a user code for arming the system. The user can also partially arm the system by just pressing the stay or special keys. This simplicity and ease-of-use gives greater confidence to the user and can reduce service calls for additional training.

2-BUTTON PANIC KEYS

The 692 keypad's top row of function keys can be used as 2-button panic keys to let the user easily send Panic, non-medical emergency, or fire reports to the central station. A label is provided to identify the correct keys to the user.

KEYBOARD BACKLIGHTING

The 692 also illuminates the keyboard in green whenever a key is pressed or the internal buzzer sounds. This allows users to easily enter their code or perform a command function in low light conditions.

SPECIFICATIONS

Operating Voltage	8.5 to 15.0 VDC
Operating Current	30mA Standby, 70mA Alarm
Dimensions	6.8" W X 5.0" H X 1.1" D
Mounting Options	Surface, 4-square, or 3-gang switch box
Colors	Ivory, White, Black, and Red

PANEL COMPATIBILITY

- XRSuper6 Command Processor™ Panel
- XR20 Command Processor™ Panel
- XR40 Command Processor™ Panel

ACCESSORIES

- 695 Keypad Conduit Backbox
- 696 Keypad Backbox
- 699 Keypad Deskstand
- LED Keypad Housing
- WR-0004 Replacement Harness



800-641-4282

www.dmp.com

Made in the USA

INTRUSION • FIRE • ACCESS • NETWORKS

2500 North Partnership Boulevard

Springfield, Missouri 65803-8877