

3.3 Wiring

Before beginning to wire the unit, ensure that all power (AC transformer and battery) is disconnected from the control panel.

To complete keypad wiring, connect the four Combus wires to the red, black, yellow and green keypad wires.

3.4 Applying Power

Once all wiring is complete, apply power to the control panel. Connect the battery leads to the battery, then connect the AC transformer. For more information on control panel power specifications, see the control panel Installation Manual.

NOTE: Do not connect the power until all wiring is complete.

4. Enrolling the Keypad

Once all wiring is complete, the module must be enrolled on the system. For instructions on enrolling keypads, see your PC4010/4020 Installation Manual.

5. Programming the Keypad

Various programming items pertain to the operation of the keypad. See your PC'4010/4020 Installation Manual for descriptions of the following programmable features:

- Partition and Global keypad options
- Keypad time-out
- Keypad blanking
- Fire, Auxiliary and Panic Keys
- Keypad lockout
- Keypad tampers (this feature must be enabled if using tamper version keypads)

MAXSYS™

LCD4520/4520T


Installation Instructions

1. Introduction

The LCD4520 keypad, for use on Maxsys PC4010CF/4020CF, presents system status via a 32-character liquid crystal display.

2. Specifications

- Connects to control panel via 4-wire Combus
- Current Draw: 50mA (from Combus)
- Optional tamper version (LCD4520T)
- Armed (red) and Trouble (yellow) status lights



3. Installation

3.1 Unpacking

The LCD4520 package includes the following parts:

- One LCD4520 keypad
- Four mounting screws
- One keypad inner door label
- One set of Fire, Auxiliary and Panic key labels

3.2 Mounting

The Keypad should be mounted where it is accessible to designated points of entry/exit. Once a dry and secure location is selected, perform the following steps to mount the keypad:

1. Remove the keypad backplate by loosening the screws located at the base of the unit.
2. Secure the keypad backplate to the wall in the desired location. Use the screws provided.

Before mounting the keypad to its backplate, complete keypad wiring.



©1998 Digital Security Controls Ltd.
1645 Flint Road, Downsview, Ontario, Canada M3J 2J6
(416) 665-8460 • Fax (416) 665-7498 • 1-800-387-3630
Printed in Canada 29002888 R0

Please refer to the System Installation Manual for information on limitations regarding product use and function and information on the limitations as to liability of the manufacturer.