



NAPCO®

333 Bayview Avenue
Amityville, New York 11701
For Sales and Repairs, (800) 645-9445
For Technical Service, (800) 645-9440

© NAPCO 2003

GEM-P1632 AND GEM-P816 VERSION 10A GUARDIAN QUICK START

WI1215 5/03

The GEM-P1632 panel version 10A allows direct address programming of the Test Timer function. To send an automatic Test Timer report to the central station, use a GEM-K1CA keypad to program the new addresses as follows:

A: ENABLE TEST TIMER REPORT

Since you wish to send a *Report Event Telco 1* response when the Test Timer event occurs, enable the "Report Event Telco 1" (address 0464) for Test Timer as follows:

Enable Test Timer Report to Telco 1:

1. Enter Direct Address Program Mode. Address "0000" will display.
2. Press to access Address 0464.
3. Press . The number "1" will appear on the display indicating the Test Timer system event is entered.
4. Press to save. A report will now be sent to Telco 1 when a Test Timer event occurs.

B: SET DAY OF THE WEEK

See the chart at right (address 9997) to select which day(s) you wish to send an automatic Test Timer report.

1. Press to access Address 9997.
2. Press the number which corresponds to the day(s) you wish to send a Test Timer event. Each number will appear in the keypad display when pressed indicating the days selected.
3. Press to save.

9997	Test Timer Day of Week	
Default		Option
OFF	1	SUNDAY
OFF	2	MONDAY
OFF	3	TUESDAY
OFF	4	WEDNESDAY
OFF	5	THURSDAY
OFF	6	FRIDAY
OFF	7	SATURDAY
OFF	8	RESERVED

C: SET TIME OF DAY

See the charts below to select the hour (address 9998) and minute (address 9999) in which to send the automatic Test Timer report. **Note:** You must program first the hour and then the minute. Enter the time in 24-hour format.

HOUR

Test Timer Hour	ADDRESS 9998	
	<input type="text"/>	<input type="text"/>

[Enter Values: 01-23]

MINUTE

Test Timer Minute	ADDRESS 9999	
	<input type="text"/>	<input type="text"/>

[Enter Values: 01-59]

1. Press to access address 9998.
2. Enter the **hour** to send the Test Timer event. *For example, to set the time of 9:30PM, the 24-hour equivalent is "21:30". Therefore, in address 9998, enter the decimal "21" for the hour.*
3. Press to save.
4. Press to access address 9999.
5. Enter the **minute** to send the Test Timer event. *To set the time of 9:30PM, the 24-hour equivalent is "21:30". Therefore, in address 9999, enter the decimal "30" for the minute. The number "30" will now appear in the keypad display.*
6. Press to save both the hour and minute. Press to exit Direct Program Mode.

Note: The updated hour (address 9998) will not appear in the display (and will not be updated) until the minute is entered and updated also.