

GENESYS 824 ALPHA - INSTALLER PROGRAMMING SHEET

3440-0242
OPTEX INC.
Torrance, California

ZONE	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24
MEMORY LOCATION	0 0	0 2	0 4	0 6	0 8	1 0	1 2	1 4	1 6	1 8	2 0	2 2	2 4	2 6	2 8	3 0	3 2	3 4	3 6	3 8	4 0	4 2	4 4	4 6

Default																									
00	Zone Type - Loop Type *1	2	2																						
00A	Loop Response	0	5																						
00B	Alarm Code	0	0																						
00C	Trouble Code	0	0																						
00D	Bypass Code	0	0																						
00E	Restore Code	0	0																						

00F ZONE FEATURES

1	TELEPHONE	YES																							
2	AUDIBLE	YES																							
3	PULSE BELL	NO																							
4	PGM 1	NO																							
5	PGM 2	NO																							
6	WALK TEST	YES																							
7	MONITOR	YES																							
8	SILENT DAY	NO																							

00G ZONE FEATURES

1	KEYPAD 1 AUDIBLE	YES																							
2	KEYPAD 2 AUDIBLE	YES																							
3	KEYPAD 3 AUDIBLE	YES																							
4	KEYPAD 4 AUDIBLE	YES																							
5	DISPLAY ARMED	YES																							
6	SHUNT ALLOWED	NO																							
7	BYPASS ALLOWED	YES																							
8	RADIO OUTPUT	NO																							

* 1

Zone Type	Loop type	ARMING MODE	ENTRY/EXIT 1 and 2	PERIMETER INSTANT	INTERIOR #1	INTERIOR #2	INTERIOR #3
0 - ENTRY - EXIT 1	0 - NORMALLY OPEN	AWAY	Delayed Exit Delayed Ent	Delayed Exit Instant	Delayed Exit Follower or Instant	Delayed Exit Follower or Instant	Delayed
1 - ENTRY - EXIT 2	1 - NORMALLY CLOSED						
2 - PERIMETER INST	2 - NORMALLY OPEN - NORMALLY CLOSED	STAY	Delayed Exit Delayed Ent	Delayed Exit Instant	Delayed Exit Follower or Instant	Bypassed	Delayed
3 - INTERIOR 1	3 - N.O. - SUPERVISED W/EOL - reports trouble on break, alarm on short						
4 - INTERIOR 2	4 - N.C. - SUPERVISED W/EOL - reports trouble on short, alarm on open	INSTANT	Instant Always	Instant Always	Instant Always	Bypassed	Delayed
5 - INTERIOR 3							
6 - 24 HOUR							
7 - FIRE 24 HOUR							
8 - DAY CIRCUIT							