



RF3341 Wireless Keypad



- ▶ **Compatibility with the RF3224 and RF3222 Receivers**
- ▶ **Backlighting and key-press sounder**
- ▶ **Portable or mounted usability**
- ▶ **Panel relay or output control**
- ▶ **Factory programmed transmitter ID for quick and simple transmitter enrollment**
- ▶ **Three programmable keys**
- ▶ **One programmable option key**

The RF3341 is a one-way wireless keypad transmitter with backlighting and key-press sounder, which allows the user to arm, or disarm, and send special codes anywhere within the range of the system receivers. The RF3341 is compatible with the RF3224 Receiver and with the RF3222 Receiver. The keypad can be wall mounted or portable. Control panel programming and control panel type determine which system functions are available from the wireless keypad.

Functions

Programmable Keys

Three programmable keys are available. Summon fire, police, or emergency department personnel. A sliding cover protects the programmable keys so that you do not accidentally press them. Press the programmable keys for two seconds to transmit a message. At the end of the two seconds, the keypad beeps once to indicate that it sent a message to the alarm system.

Programmable Option Key

Program option key to control other devices such as lights.

Certifications and Approvals

Listings and Approvals:	Industry Canada
Complies with:	Federal Communications Commission (FCC ESV-0407-3)

Installation/Configuration Notes

Compatibility Information

Receivers	Control Panels
RF3212	Solution Ultima 844, 862, and 880, CC488
RF3213	VR-8
RF3222	DS7400XIV4
RF3224	DS7240, DS7220, D6412, and D4412

Parts Included

Quant.	Component
1	Wireless keypad
1	Wall Mounting Bracket

Technical Specifications

Mechanical Properties

Dimensions

Keypad:	11.8 cm x 5.8 cm x 2.3 cm (4.65 in. x 2.3 in. x 0.9 in.)
Keypad Base:	13.0 cm x 7.2 cm x 1.5 cm (5.1 in. x 2.85 in. x 0.6 in.)

Environmental Considerations

Relative Humidity:	0% to 95% (non-condensing)
Temperature (operating):	-29°C to +65°C (-20°F to +150°F)

Power Requirements

Batteries:	3 V lithium battery
Battery Life:	Up to 3 years under normal operating conditions with recommended battery types
Recommended Battery Types:	Duracell® DL123A, Panasonic® CR123A, or SANYO® CR123A

Trademarks

Duracell® is a registered trademark of the Gillette Company, USA, in the United States and/or other countries.

Panasonic® is a registered trademark of a Matsushita Electric Industrial Co., Ltd.

SANYO® is a registered trademark of SANYO North America Corporation.

Ordering Information

RF3341 Wireless Keypad	RF3341
------------------------	--------

Europe, Middle East, Africa:
 Bosch Security Systems B.V.
 P.O. Box 80002
 5600 JB Eindhoven, The Netherlands
 Phone: +31 40 2577 284
 Fax: +31 40 2577 330
 emea.securitysystems@bosch.com
 www.boschsecurity.com

Americas:
 Bosch Security Systems, Inc.
 130 Perinton Parkway
 Fairport, New York, 14450, USA
 Phone: +1 800 289 0096
 Fax: +1 585 223 9180
 security.sales@us.bosch.com
 www.boschsecurity.us

Asia-Pacific:
 Bosch Security Systems Pte Ltd
 38C Jalan Pemimpin
 Singapore 577180
 Phone: +65 6319 3450
 Fax: +65 6319 3499
 apr.securitysystems@bosch.com
 www.boschsecurity.com

Represented by