



Introduction

This is the *NetworkX User Addendum (466-2267A)* for the following documents:

- *NX-4V2/NX-4V2-APT Installation Manual (NX4V2IB05)*
- *NX-6V2/NX-6V2-APT Installation Manual (NX6V2ID05)*
- *NX-8V2/NX-8V2-AES Installation Manual (NX8V2IF05)*
- *NX-8E/NX-8E-CF Installation Manual (NX8EIK05/NX8ECF-IM)*

This document includes new information on this product that did not make it into the manual. Where information differs between the two documents, this document supersedes the manual.

What's new

Daylight saving time programming, Location 84, has been added to the programming locations.

Note: Version 1 NetworkX controls do not support daylight saving time.

This programming location contains data that affects when daylight saving time begins and ends. This will happen at 2:00 a.m. on the day programmed. The default is to begin daylight saving time on the second Sunday in March and end daylight saving time on the first Sunday in November.

Segment 1. Daylight saving time starting month (1 to 12). The default is 3.

Segment 2. Daylight saving time starting Sunday. (1 to 4 indicates the first to fourth Sunday of the month; greater than 4 indicates the last Sunday of the month.) The default is 2.

Segment 3. Daylight saving time ending month (1 to 12). The default is 11.

Segment 4. Daylight saving time ending Sunday. (1 to 4 indicates the first to the fourth Sunday of the month; greater than 4 indicates the last Sunday of the month.) The default is 1.

Note: The defaults above are set to conform to the daylight saving start and end times beginning in 2007.