



# APPENDIX A CENTRAL STATION 4/2 FORMAT REPORTING

If you are using 4/2 reporting format and the central station is using a CS-4000 for monitoring, the CS-4000 handles the incoming reports as described in Table A.1. In addition, the first digit of the Panel account number is not reported in 4/2 format, so if the account number is programmed as 57-234, the CS-4000 displays the account as X7-234. For more information about the CS-4000, see the CS-4000 Central Station Receiver Installation and User's Manual (46-036).

C 2000  
Panel

**Notes:** Panels do not send restore reports except for upper sensor numbers 90 and 91. See Table A.1.

**Table A.1. 4/2 Reporting Format**

Description	System Sensor	Alarm Code	Trouble Code	Cancel Code	Restore Code
Sensor Number 1	01	01	B1	39	
Sensor Number 2	02	02	B2	40	
Sensor Number 3	03	03	B3	41	
Sensor Number 4	04	04	B4	42	
Sensor Number 5	05	05	B5	43	
Sensor Number 6	06	06	B6	44	
Sensor Number 7	07	07	B7	45	
Sensor Number 8	08	08	B8	46	
Sensor Number 9	09	09	B9	47	
Sensor Number 10	10	10	C0	48	
Sensor Number 11	11	11	C1	49	
Sensor Number 12	12	12	C2	50	
Sensor Number 13	13	13	C3	51	
Sensor Number 14	14	14	C4	52	
Sensor Number 15	15	15	C5	53	
Sensor Number 16	16	16	C6	54	
Sensor Number 17	17	17	C7	55	
Sensor Number 18	18	18	C8	56	
Touchpad Fire Emergency	80	80		F2	
Touchpad Police Emergency	81	81		F3	
Touchpad Auxiliary/Medical Emergency	82	82		F4	
Manual Phone Test	83	83			
Opening Report	84	84			
Closing Report	85	85			
Duress Alarm	86	86			
Forced Armed Auto	87	87			
RF Touchpad Low Battery or Supervisory	89		F9		

Table A.1. 4/2 Reporting Format (Continued)

Description	System Sensor	Alarm Code	Trouble Code	Cancel Code	Restore Code
AC Power Failure	90	90			FC
Low Panel Battery	91	91			FD
Panel Tamper	92	92		FS	
Automatic Phone Test	93	93			
Receiver Failure	94	94			
Panel Back In Service	95	95			
Phone Failure	96	96			
Auto Event Buffer Dump	98	98			