

# Adding a Sensor to Your System

Sensors, Detectors and Key FOBs that are **not included** with your Security kit need to be **Added** into your system. **Adding** a sensor means that your Control Panel will be in communication with your new Sensor, Detector or Key FOB.

It is very easy to do and the “voice prompt” system will “talk” back to you each step of the way! If you make a mistake before step #9, simply press the **Cancel** button and start over!

## Procedure for Adding a Sensor, Detector or Key FOB

- 1 Open front cover of the Control Panel and place the provided template over the buttons.
- 2 Enter your ID \_\_\_\_\_ (default ID is **4321**).
- 3 Push the **Add** button.
- 4 Push the **1** button.
- 5 Push the “button” on the sensor. See **Locating Sensor Buttons** document.
- 6 Push **0** button repeatedly until you hear the location you want to select for that sensor.
- 7 Push the **Done** button.
- 8 Push number buttons for the **Sensor Group**:

Exterior Door Sensor: **1, 0**

Interior Door Sensor: **1, 4**

Window Sensor: **1, 3**

Interior Motion Sensor: **1, 7**

Glass Break Sensor: **1, 3**

Key FOB (Key Chain Remote): **0, 1**

Smoke Detector: **2, 6**

Carbon Monoxide Detector: **3, 4**

Panic Button - Pendant: **3, 4**

Panic Button - Wrist: **3, 4**

- 9 Push the **Done** button. You're finished!

